

(19)



Europäisches Patentamt

European Patent Office

Office européen des brevets



(11)

EP 0 619 024 B1

(12)

EUROPEAN PATENT SPECIFICATION(45) Date of publication and mention
of the grant of the patent:

25.03.1998 Bulletin 1998/13

(51) Int Cl.⁶: **G01S 15/60, G01S 15/58,
G01S 15/10**(21) Application number: **94901194.4**(86) International application number:
PCT/US93/10203(22) Date of filing: **22.10.1993**(87) International publication number:
WO 94/10583 (11.05.1994 Gazette 1994/11)**(54) CORRELATION SONAR SYSTEM**

Sonarsystem mit Korrelation

SYSTEME SONAR DE CORRELATION

(84) Designated Contracting States:

AT BE CH DE DK ES FR GB GR IE IT LI NL PT SE

(56) References cited:

EP-A- 0 010 974**WO-A-92/05456****US-A- 5 122 990**(30) Priority: **23.10.1992 US 966092**

(43) Date of publication of application:

12.10.1994 Bulletin 1994/41(73) Proprietor: **ROWE, DEINES INSTRUMENTS
INCORPORATED****San Diego, CA 92131 (US)**

(72) Inventors:

- **BRADLEY, Steven, E.**
San Diego, CA 92124 (US)
- **ROWE, Francis, D.**
San Diego, CA 92117 (US)

(74) Representative: **Fiener, Josef et al**
Patentanwälte**Kahler, Käck, Fiener et col.,**
P.O. Box 12 49
87712 Mindelheim (DE)

- **JOURNAL OF THE ACOUSTICAL SOCIETY OF AMERICA vol. 92, no. 3, 1 September 1992, NEW YORK US pages 1692 - 1698 XP307201 SUTTON ET AL 'ACOUSTIC BEDLOAD VELOCITY ESTIMATES USING A BROADBAND PULSE-PULSE TIME CORRELATION TECHNIQUE'**
- **PROCEEDINGS OF THE IEEE FOURTH WORKING CONFERENCE ON CURRENT MEASUREMENT 1 August 1990, CLINTON MD., USA pages 306 - 313 XP214389 BRADLEY ET AL. 'ACOUSTIC CORRELATOR CURRENT PROFILER'**
- **IEEE TRANSACTIONS ON ULTRASONICS, FERROELECTRICS AND FREQUENCY CONTROL vol. 38, no. 1, 1 January 1991, NEW YORK US pages 17 - 26 XP172452 FERRARA ET AL 'A NEW WIDEBAND SPREAD TARGET MAXIMUM LIKELIHOOD ESTIMATOR FOR BLOOD VELOCITY ESTIMATION- PART II: EVALUATION OF ESTIMATORS WITH EXPERIMENTAL DATA'**

Note: Within nine months from the publication of the mention of the grant of the European patent, any person may give notice to the European Patent Office of opposition to the European patent granted. Notice of opposition shall be filed in a written reasoned statement. It shall not be deemed to have been filed until the opposition fee has been paid. (Art. 99(1) European Patent Convention).

EP 0 619 024 B1

Description

Background of the Invention

5 Field of the Invention

The present invention relates to velocity measurement systems and, more particularly, to such systems applying correlation methods.

10 Description of the Related Technology

There is a class of systems that measure distance or velocity with sound waves. These systems include underwater sonar and medical imaging equipment (hereinafter generally referred to as "sonar systems"). Underwater sonar systems, in particular, may be manifested as current profilers, velocity logs, and so forth.

15 A current profiler is a type of sonar system that is used to remotely measure water velocity over varying ranges. Current profilers are used in freshwater environments such as rivers, lakes and estuaries, as well as in saltwater environments such as the ocean, for studying the effects of current velocities. The measurement of accurate current velocities is important in such diverse fields as weather prediction, biological studies of nutrients, environmental studies of sewage dispersion, and commercial exploration for natural resources, including oil.

20 Typically, current profilers are used to measure current velocities in a vertical column of water for each depth "cell" of water up to a maximum range, thus producing a "profile" of water velocities. The general profiler system includes a transducer to generate pulses of sound (which when downconverted to human hearing frequencies sound like "pings") that backscatter as echoes from plankton, small particles, and small-scale inhomogeneities in the water.

25 Two important types of sonar technology that may be used for current profiling are Doppler and correlation. The basic concept of velocity measurement using signal correlation has been known for many years. For example, in 1964, Dickey, Jr. was issued U.S. Patent No. 3,147,477 ("Dickey '477") disclosing a system to measure speed including a source of wave energy (or transmitted signal) directed toward a body, multiple receiving devices having a known separation for receiving echoes from the body, correlating means including time delay means, and speed determining means dependent on the quotient of the receiver separation and the time delay. Although the patent document describes an embodiment of a correlation system for an aircraft using radar (electromagnetic signals), it suggests a correlation system for a water-going vessel using sonar (sound signals).

30 A correlation system inherently requires that the transmitted signal must have some similarity with itself to achieve a maximum correlation at the specified time delay. A correlation system was disclosed by Roeder, et al. (U.S. Patent No. 4,103,302) wherein signal similarity was achieved by generating a pulse train, or series of repeating pulses. According to the disclosure, the use of repeating pulses provides advantages over the continuous wave (CW) system described in Dickey '477 including: a simplified transmission source, insensitivity to variations in attitude of the conveying vehicle, and improved accuracy and reliability derived from digital electronics.

35 U.S. Patent No. 4,244,026 to Dickey, Jr., ("Dickey '026") corresponding to EP-A-0 010 974 discusses a correlation system using a pulse train from which complex correlation values are employed in velocity measurement. According to Dickey '026, the method of signal processing the complex correlation values estimates components of location by specifically requiring the steps of processing the correlation values as samples of a continuous function of position and curve fitting the samples to the magnitude or real part of the continuous, spacial correlation function to provide an estimate of the peak value of correlation magnitude. Thereafter, the location components at the correlation peak are divided by twice the pulse repetition period of the pulse train to obtain velocity measurements. This signal processing is described in the specification of Dickey '026 at col. 13, lines 7-40.

45 As previously noted, correlation sonar technology can be used in current profilers. In designing a current profiler, in particular, trade-offs are made among a variety of factors, including maximum profiling range and temporal, spacial (the size of the depth cell), and velocity resolution. Temporal resolution refers to the time required to achieve a velocity estimate with the required degree of accuracy. In typical applications, a current profiler will make a series of measurements which are then averaged together to produce a single velocity estimate with an acceptable level of velocity variance, or squared error.

50 Over the past ten years, acoustic Doppler technology has been successfully developed for short- and medium-range current profiling applications such as measuring sediment movement in rivers and estuaries. To achieve the longer ranges necessary to study water velocities at deep ocean depths, lower frequencies must be used so that energy losses due to sound absorption by the water can be kept at manageable levels. Although there is no fundamental limitation in the Doppler technology that prevents the use of lower frequencies, there is a practical constraint due to the large size of the acoustic transducers required for these lower frequencies. Existing correlation sonar techniques measure current velocities by transmitting two short pulses from a relatively smaller transducer along a correspondingly

wider angle acoustic beam. By careful cross-correlation of spatially sampled returns it is possible to determine the displacement of the acoustic targets within the beam from one pulse to the next, and hence, compute their average velocity. The primary advantage of a correlation sonar is that for comparable sized systems, the correlation sonar is able to utilize a lower frequency regime and, therefore, potentially gains substantial current profiling range.

Acoustic bedload velocity estimates using a broadband pulse-pulse time correlation technique" by D. Sutton and J. Jaffe, 1992 ("Sutton") discusses a broadband correlation sonar system using multiple transducers and pulses. In Sutton, one receiver time series is autocorrelated in time (i.e., one pulse is autocorrelated to a later pulse). This autocorrelation is used in a maximum likelihood algorithm which is capable of finding only one vector component of the three-axis velocity vector. This is a fundamental principle of traditional Doppler sonars, in general. In order for the full three-axis velocity vector to be determined, it is necessary to have separate beams of sound directed toward (in general) different sections of the seabed producing different stochastic time series for each beam. The ML method is then applied to each time series in isolation to produce one vector component velocity from each time series in isolation. To form the full three-component velocity vector, individual ML estimates are later combined by virtue of the fact each one represents a component of velocity in a different direction.

Nonetheless, it is only recently that the computational burden required of sophisticated signal processing methods, required for accurate correlation processing, has been made feasible by advances in the semiconductor and computer architecture fields. The improved signal processing should include a means for bottom tracking so that the correlation sonar can also serve as a navigation device. It would also be desirable to allow individual users the flexibility of selectively trading off standard deviation and profiling resolution so as to maximize range.

Summary of the Invention

The above-mentioned needs are satisfied by the present invention which includes a correlation sonar system utilizing a monopulse transmission method and a maximum likelihood method of signal processing as defined in claim 1, 9 and 19, respectively.

In the presently proposed embodiment of the invention, the correlation system performs the functions of a current profiler, which measures current velocities in a water column, and a bottom tracker, which measures vessel velocity relative to the bottom of a body of water, such as the ocean. Basically, the present inventive system begins making velocity measurements by transmitting a single, uninterrupted acoustic pulse into the water. This pulse is of a long duration so as to not only provide a correlation delay that is less than the pulse width, but also so as to typically simultaneously ensnare all of the "scatterers" on the bottom.

The single pulse is typically transmitted for a sufficient duration to encompass both the range of temporal delays to all scatterers in the water column cell (and the bottom) as well as the temporal delay for correlation processing. The single pulse may be coded, using phase encoding, for example, for the purpose of reducing the noise variance on the measured velocity.

The pulse echoes produced when the pulse encounters small-scale inhomogeneities in the water, and then the bottom, are received by a set of transducers. The pulse echoes received by the transducers are represented internally to the system as complex values. These complex values derived from each transducer are cross-correlated with those from other transducers at different time lags (typically zero and tau) in all possible permutations to form complex correlation values. In this manner, both spatial and temporal information is derived from the process.

The complex correlation values are not converted to correlation magnitudes but rather the complex correlation values, which retain explicit phase information, are used to form a probability function. Hypothesized parameters, such as signal-to-noise ratio, seabed slope angles, parameters characterizing seabed roughness, and three component velocity (v_x , v_y , v_z), are combined with the complex correlation values to obtain a probability. The combining of hypothesized parameters and complex correlation values into a probability is accomplished mathematically using a conditional probability density function (for example, see equation B.15 on p. 348 of Statistical Theory of Signal Detection, Carl Helstrom, Pergamon Press, 1968). Hypothesized parameters are then adjusted by a model to maximize the probability. This method is appropriately known as the maximum likelihood method.

Typically, the complex values are correlated at zero lag and at the autocorrelation lag where there is a peak in the autocorrelation of the pulse and, in addition, there may be some utility in correlating at other lags as well. Consequently, a set of transmission code sequences may be stored so that one among the set may be selected based on altitude or cell resolution requirements and pursuant to an autocorrelation lag that may be the most appropriate to use for a given range of speeds.

These and other objects and features of the present invention will become more fully apparent from the following description and appended claims taken in conjunction with the accompanying drawings.

Brief Description of the Drawings

Figure 1 is a schematic representation of a water-going vessel utilizing means for generating multiple pulse sound energy into the water;

Figure 2 is a simplified waveform diagram corresponding to the method of sound transmission shown in Figure 1;

Figure 3 is a schematic representation of a water-going vessel utilizing means for generating monopulse sound energy into the water;

Figure 4 is a simplified waveform diagram corresponding to the method of sound transmission shown in Figure 3;

Figure 5 is a schematic representation of a typical correlation sonar scenario wherein a water volume, followed by a seabed, is ensonified by a pulse having a temporal autocorrelation peak at a time lag of τ_c ;

Figure 6 is a plot of the autocorrelation function of one preferred 300 element coded pulse of the present invention wherein the X-axis is defined as code lag in elements and the Y-axis is defined as a unitless autocorrelation coefficient;

Figure 7 is an example plot of the log amplitude response of an echo at various depths indicating the difference between the true seabed reflection and secondary reflections that are distinguished by a bottom tracking portion of the present invention;

Figure 8a is a scatter diagram of an exemplary current profile produced by a preferred correlation sonar embodiment of the present invention showing the East/West profile plotted as a function of depth;

Figure 8b is a scatter diagram of an exemplary current profile produced by a preferred correlation sonar embodiment of the present invention showing the North/South profile plotted as a function of depth;

Figure 8c is a scatter diagram of an exemplary current profile produced by a preferred correlation sonar embodiment of the present invention showing the vertical profile plotted as a function of depth;

Figure 9a is a side elevational view of one preferred mechanical assembly for a correlation sonar embodiment of the present invention;

Figure 9b is a top plan view of the mechanical assembly for the correlation sonar system shown in Figure 9a;

Figure 10 is a block diagram of the correlation sonar system shown in Figures 9;

Figure 11 is a flow diagram of the computer software for the correlation sonar system as executed in the electronics assembly shown in Figure 10; and

Figure 12 is a flow diagram of the computer software for the maximum likelihood function shown in Figure 11.

Detailed Description of the Preferred Embodiments

Reference is now made to the drawings wherein like numerals refer to like parts throughout. The following Detailed Description is organized into sections I - V. Section I discusses alternative pulse generation techniques that may be used in the present invention. Section II presents the presently preferred correlation sonar hardware. Section III reviews maximum likelihood estimation principles. Section IV discusses several methods to calculate the model correlation matrix as a function of unknown parameters. Section V describes the operation of the presently preferred correlation sonar. The following discussion particularly describes one presently preferred correlation sonar; however, it will be understood that the present invention includes other types of correlation systems as well.

I. PULSE GENERATION DISCUSSION

Figure 1 is an idealized correlation sonar scenario showing a water-going vessel 100 afloat in a body of water 102 having a bottom 104. The vessel 100 employs a multiple pulse, correlation sonar system (not shown), having two receivers, to track the bottom 104 and determine vessel velocity. The system transmits a first narrow pulse 106, to identify a small range spread of scatterers on the bottom 104, and then repeats to generate a second narrow pulse 108 to achieve the desired correlation in the transmitted signal at a predetermined processing delay. The two pulses 106, 108 maintain a distance relationship of τ_c , the pulse repetition interval, times the speed of sound in water, C.

For instance, Figure 2 demonstrates the concept of a repeated pulse transmission wherein, at two receiver locations on the forward ("fwd") and aft portions of the vessel 100 (Figure 1), a pulse echo pair 106' and 108', corresponding respectively to the first and second pulses 106, 108, will be highly correlated when the ship is moving forward with velocity approximately equal to the distance of separation between the two receivers divided by twice the time interval between the two transmitted pulses. Note on the top line of Figure 2, time increases to the left (i.e., pulse 108 is generated after pulse 106); whereas in lines two and three, time increases to the right (i.e., reception of 106' and 108' occur after reception of 106' and 106", respectively).

The resolution of the differential range to the bottom scatterers 104 which can be simultaneously illuminated is limited by the width of the pulses 106, 108 (Figure 1). This causes the initial portion of the return echo 106' (and 106") to come from a center point on the bottom 104 below the sonar system first and then later portions of return echo 106'

(and 106") comes from scatterers on the bottom 104 that are offset from the point and thus at a greater range from the system than the center point. After a period of time, the system views the scatterers that are beyond the transmitter beamwidth and the signal level fades away as indicated by the ramped shape of the final portion of the received echo 106' (and 106") in Figure 2. At a later time, a second pulse 108 hits the bottom 104 and the scenario repeats.

Because the received signal level attenuates over time, or in other words, the leading portion of the echo is substantially different from the trailing portion, the correlation delay of the multiple pulse system (i.e., the time between pulses, τ_c) should be equal to or longer than the bottom illumination time (i.e., the pulse width). If it were otherwise, the system would estimate velocity at significantly reduced precision caused by interpulse interference.

The timing of the preferred single pulse, or monopulse, transmission of the present invention is quite different from the multiple pulse system. Figure 3 shows a scenario similar to Figure 1; however, in Figure 3 the vessel 100 employs a monopulse correlation system. A simplified pulse waveform of the presently preferred system is shown in Figure 4. The width of a single transmitted pulse 110 is typically long compared to the range spread to the scatterers on the bottom 104 (Figure 3). The single return echo 110', 110" received by the forward and aft receivers corresponds roughly in length to the transmitted pulse 110 and, hence, the scatterers on the bottom 104, inside the beamwidth, are typically all viewed simultaneously.

In general, the single pulse is coded, e.g., phase coding, to have a pre-specified autocorrelation peak. The modulation, or coding, on the return echo 110" of the aft receiver is shifted in time, or delayed, compared to the echo 110' received by the forward ("fwd") receiver. This time shift is indicative of the period of time that the vessel 100 traverses a distance equal to one-half the distance between the receivers. Therefore, the correlation delay of the presently preferred system must always be less than the width of the single pulse which is to be contrasted with the multiple pulse technique that is typically greater than or equal to the pulse width.

Figure 5 shows a typical correlation sonar scenario. The water volume in a beam 112 and the seabed 104, which has an "effective" tilt as measured by angles α and β , is ensonified by a coded pulse created by a relatively wide beam acoustic transducer (not shown) of width θ and center frequency f_0 . The nature of a single, coded pulse is such that the autocorrelation function of the pulse possesses a temporal autocorrelation peak at a predetermined time lag of τ_c . The returning pressure waves are monitored in time at differing spatial locations. Note that at a given instant in time, only scattering centers which reside within a series of ring-like structures, e.g., 114 on the seabed 104 are received. As time increases, the radius of these rings will increase. The signal return from one receiver at a time, t , will be highly correlated with the return from another receiver at a time $t + \tau_c$ provided that the scatters have moved exactly one-half the spatial vector difference between the two receivers in a time τ_c .

This effect is referred to as "waveform invariance". Equivalently, "waveform invariance" implies that the time domain return from a series of stationary scatterers depends not on the exact location of the transmitter and receiver, but rather only on the midpoint of the line segment which joins the transmitter and receiver. The principle of waveform invariant geometry assumes only that the vertical distance to the scatterers is large compared to the transducer element separation. For the correlation sonar, the transducer separations are typically of the same order of magnitude as the wavelength of sound, and therefore this approximation applies in almost every conceivable case. Another interesting feature of waveform invariance is the complete lack of any dependence of the horizontal velocity on the speed of sound in the water.

The signals received by two different transducers can be cross-correlated with a time lag, τ_c , corresponding to the autocorrelation peak of the transmitted pulse. By utilizing a variety of receiver transducers which have different mutual spatial separation vectors, it is possible to search for the vector displacement corresponding to the maximum of the correlation function.

The real situation for the correlation sonar is more complicated. Roughly, the location of the maximum of the amplitude of the correlation function contains information about the "horizontal" velocity, while the corresponding phase of the correlation function contains information about the "vertical" velocity. However, the maximum likelihood signal processing algorithm used by the present invention estimates the velocity through a means which does not seek to locate the peak of the magnitude of the correlation function nor determine phase under the peak, but rather incorporates all available correlations in their full complex form to determine the most likely velocity vector. Additional complications must be addressed concerning signal-to-noise ratio (SNR) values and possible sensor pitch and roll changes between transmit and receive. For example, the angles α and β are related to an "effective" seabed tilt and/or transducer tilt due to vessel movement. The angles α and β also contain information regarding the beam patterns of the transmitter and receivers as well as the angular scattering strength of the seabed. These additional complications tend to slightly modify the α and β angles to "effective" α and β angles which are slightly different from the physical angles which geometrically relate the sensor coordinate system to the seabed coordinate system. Hence, one key to a successful correlation sonar velocity log function of the present invention is in the optimal estimation of the unknown three-axis velocity vector from the different complex cross-correlation functions formed from the data collected by the numerous receivers.

Referring now to Figure 6, the use of a coded pulse in the presently preferred correlation system provides auto-

correlation properties that allows code subsections to be similar but not necessarily identical. Moreover, such encoding is not used to achieve improved spatial resolution (it is used to improve noise averaging) and thus the waveform is not encoded so as to achieve the same function as a repetitive pulse. In fact, non-identical code sections are sometimes deliberately constructed to provide zeroes on either side of the desired autocorrelation peak lag which reduce the corruption of velocity estimates which may be caused by autocorrelation side-lobe biases.

Pulse coding techniques are capable of placing more energy into the water to be available for scattering while maintaining the necessary correlation properties at a time lag τ_c . It is possible to take advantage of this technique to increase the energy content of the pulse packet while maintaining the high bandwidth of the system. Placing more energy per ping into the water is essential to increase the range performance of the present correlation sonar system.

Figure 6 shows one preferred encoded pulse. The primary pulse coding technique presently used involves pseudo-random codes which are now generated by a code finding program. The length of the code is specified along with the desired time delay for correlation. The computer program, run off-line from the sonar system, then searches for the optimal coded pulse sequence. The program performs many optimization searches and keeps track of the best result. The corresponding solution is then written to disk. The presently preferred modulation method is a two phase encoding scheme. The carrier phase is modulated to be either 0 or 180 degrees for each element. Figure 6 shows an example 300 element pulse code sequence which results in an autocorrelation side-lobe peak at a 101 element delay. Preferably, each pulse element represents more than two and less than ten carrier cycles.

The presently preferred code finding process is described as follows. First, a random code is generated using well-known methods. The autocorrelation function for the initial random code is calculated. A figure of merit based on the autocorrelation function is then calculated. The figure of merit is related to the sum of squares of all heights divided by the square of the height at desired peak or time delay for correlation. The best values for merit are low, and generally near 1.

Multiple trials are conducted, wherein each trial begins with a new random code. Within each trial, the code may be mutated and a new figure of merit, based on the mutated code, is compared with the best figure of merit for that trial. If the code is found to be better than the best for that trial, the code elements are mutated at a slow rate, usually one at a time, and a more careful search is conducted around the vicinity of the code. If no improvement is found, the number of code elements mutated is slowly increased until a predetermined number of code elements is reached. Anytime a new trial champion is found, the process slows down to mutating one element to search the neighborhood better. After a prespecified number of mutations, the champion from the current random code is saved, and the procedure begins all over again by generating a new random code.

Once a best code is found in each randomly seeded trial, it is possible to attempt to tack on some code elements at the end which will force lags on either side of the desired peak to be zero. Sometimes this procedure has no solution and the code is thrown away. If it is possible, the code elements are appended to the best code and the figure of merit for the newly formed code is compared with the existing overall champion from all trials and, if it is superior, it is saved as the new overall reigning champion.

Figure 7 illustrates an exemplary echo signal from a sonar system in water having the seabed 104 (Figure 5) at a depth of 34 meters. Subsequent to the transmission of a coded pulse, each receiver of the correlation sonar system records echo data. Before any correlations or velocity estimation can occur, the data must be searched to determine the distance to the seabed, and hence, the portion of the data to process. The seabed is detected by investigating the amplitude of the response as a function of time. In general, the return from the water volume will decrease from spherical spreading and absorption losses. At some point, the pulse will be reflected from the seabed, resulting in a large increase in backscattered strength.

A matched filter approach is used to determine the bottom range from the reflected signal. The presently preferred matched filter method is a modified version of that described in U.S. Patent No. 5,122,990 to Deines, et al., which is hereby incorporated by reference.

The example field data of Figure 7 plots the logarithm of the amplitude of the received signal as a function of apparent depth derived by multiplying $\frac{1}{2}$ the speed of sound by time. The water return quickly diminishes at the beginning of the data stream due in this case to the use of an operational frequency of 76.8 kHz and the cleanliness of the water. At a range of approximately 34 meters, the seabed reflection starts. There is a second "bump" at twice the apparent distance which corresponds to a secondary reflection of the initial transmitted pulse down to the seabed, back up to the water-air interface, down to the seabed again where it is reflected back to the receiver. Depending on the transmitted power, absorption, and depth of the seabed, tertiary and higher order multiple reflections can occasionally be observed. The width of the return is a function of the length of the transmitted pulse and the range to the seabed. Due to thermal noise, ambient noise in the water, and flow noise, the receivers always produce a finite signal corresponding to a noise floor.

II. CORRELATION SONAR HARDWARE DESCRIPTION

As previously noted, the present invention may be embodied as a correlation sonar system having current profiling and bottom tracking functions. Figures 8a, 8b and 8c show velocity measurements in a water profile according to a preferred current profiling function of the present invention. Figure 9a shows a side elevational view of the mechanical assembly, generally indicated at 202, that houses and protects the transducer electro-mechanicals used to implement the presently preferred correlation sonar of the invention. An I/O connector (not shown) is located at the back end of the transducer assembly 202 so that data can be transferred to the two other subsystems of the correlation sonar system 200 (Figure 10) via a transmission cable 220.

A top plan view of the front end of the transducer assembly 202 is shown in Figure 9b. The embodiment of the assembly 202 shown has an operational frequency of 22 kHz. However, the transducer assembly 202 is designed to be a modular unit so that other frequencies may be specified using different assembly housings according to the various sized transducers used as dictated by the selected frequency. Seven transducer elements are packed together in a hexagonal configuration (one transducer in the center of the hexagon). All seven of the hex packed elements (five labeled 208 and two labeled 210) are used as transmitter transducers. Two of the hex packed elements 210 and six other separate elements, arranged in the assembly according to an optimization of vector differences between transducers, are used as receiver transducers 210. Each transducer element 208, 210 is approximately 2" in diameter. Other numbers, sizes, spatial separations, and transmitter/receiver assignments of transducers could, of course, be configured.

The illustrated transducer assembly 202 is approximately 18" in diameter and 11" long having a weight of under 150 lbs. and a current profiling range, (with bin resolution somewhat less than a Doppler system), of around 1,200 meters, about twice the depth of a conventional 75 kHz Doppler system. By comparison, the bottom tracking range of one 75 kHz Doppler system weighing about 350 lbs. and having a length of about 1 meter, is around 1,500 meters. However, the bottom tracking range of the presently preferred 22 kHz system is 5,000 meters or 16,000 feet.

A functional block diagram of the preferred correlation sonar system 200 includes the transducer assembly 202 shown in Figure 9 and an electronics assembly 204 coupled to a host computer 214. Other designs may incorporate a microprocessor based system inside the electronics assembly 204 to eliminate the need for the separate host computer 214. In general, the correlation sonar system is conveyed on a vessel, such as the vessel 100 shown in Figure 5; however, underwater vehicles or fixed mountings, such as platform or buoy mountings, are also possible.

The transducer assembly 202 comprises the transducing elements 208, 210 which convert electrical energy into acoustic energy for transmitting code sequences, and convert received acoustic energy into electrical energy for analysis. The assembly 202 further comprises a set of tuners 216 to tune the transducing elements to operate at the proper operational frequency and impedance, and, for the receiving transducer elements, a set of receivers 218 to amplify the received signal to the appropriate level for transmission to the electronics assembly 204 through an underwater cable 220, currently a 19 mm multiply shielded cable, connected to the I/O connector (not shown) of the transducer assembly 202.

The electronics assembly 204 includes a set of four demodulator boards 222, wherein each board 222 has sine and cosine channels for two of the receiving transducers 210. The demodulator boards 222 convert the received signal into baseband (low frequency) digital sequences, thus incorporating analog-to-digital (A/D) circuitry. Presently, the complex data is hardlimited and each sample is one of four binary states contained in two bits, one bit per quadrature component of the waveform. The time interval between samples depends on the sampling rate. The sampling rate is user selectable and is normally chosen to be some factor times the bandwidth of the transducer elements considered. Typically, the sampling rate is 2 to 8 times the bandwidth. For example, in the 22 kHz system, the bandwidth is about 18% of the frequency and each coded element is six carrier cycles but, due to clipping, a sample is made every 1.5 carrier cycles. Bandwidth may be increased to obtain more information but at the expense of reduced range due to a corresponding increase in the noise.

A digital signal processor (DSP) 230, which is preferably a 16-bit Texas Instruments TMS320E15, accumulates the sequences. The DSP 230 forms cross-correlations of sequences received from the eight receivers into two or more 8×8 matrices, i.e., one correlation coefficient per receiver transducer pair, at each of the time lags, typically 0 and τ_c .

A timing generator 232 controls a power amplifier 226 to generate the appropriate coded pulse, which is generated into the water via the transmitting transducers 208. The electronics assembly 204 is powered by a power supply 236 which is regulated by a power regulator 234. The preferred correlation sonar system 200 requires less than 100 Watts of power.

The operation of certain other functional blocks, primarily the demodulators 222, the DSP 230 and the timing generator 232, in the electronics assembly 204 is coordinated by a microcomputer or CPU 228, which is preferably a CMOS 68000 microprocessor available from a number of vendors including Motorola. The host computer 214 communicates with the electronics assembly CPU 228 across a line 238, presently an RS-232 serial communications line, via an I/O port 240. The I/O port, or serial I/O board 240 connects to a computer or PC 242. It is also possible to replace

the CPU 228 with an interface card for the electronics assembly. This interface card is then connected via a cable to a PC interface board located in the host computer 214. Communication between the host computer 214 and various electronics modules (e.g., DSP 230, timing generator 232, demodulators 222) is then possible without the use of a CPU card 228. The computer 242 also includes a secondary data storage media 244, preferably either a 100 Megabyte hard disk drive, a 44 Megabyte Bernoulli box or an optical disk. The computer 242 preferably includes a floating point processor and is presently configured with a Number Smasher-860 board, available from Microway of Kingston, Massachusetts, which includes an Intel i860 64-bit, RISC architecture, microprocessor.

The computer 214 provides a convenient interface between the user and the correlation sonar system 200 by controlling various aspects of transmit, receive, storage, and analysis of data. The computer 214 allows the user to select a transmit pulse from a series of coded sequences stored on the data storage device 244, as well as define the length of the receive signal to sample. The received signal is then divided into range gated bins wherein each bin contains a water velocity which has been estimated by maximum likelihood signal processing which is described below.

III. MAXIMUM LIKELIHOOD SIGNAL PROCESSING

Subsequent to the transmission of a phase modulated pulse, each of the receivers 210 (Figure 10) record inbound pressure waves (complex values of voltage) as a function of time. The data is divided into bins wherein each bin is used to calculate a velocity estimate. The method outlined in this section is considered to be excellent at estimating the velocity; however, it is very computationally demanding.

In all the analysis presented here it is assumed that the incoming pressure is a complex Gaussian random variable as a function of time. This is justified because of the coupling between the central limit theorem and the large number of randomly placed scattering centers in the range bin of which the water velocity is being estimated. The general expression for the probability density function (PDF) of observing the data vector \mathbf{z} given the parameters were in the state, θ for n complex data points is

$$p(\mathbf{z}; \theta) = \frac{1}{\pi^n |\mathbf{R}|} \exp(-\mathbf{z}^* \mathbf{R}^{-1} \mathbf{z}), \quad (1)$$

where \mathbf{R} is the $n \times n$ correlation matrix describing how data point \mathbf{z}_i is correlated with data point \mathbf{z}_j , $|\mathbf{R}|$ is the determinant of \mathbf{R} , and $p(\mathbf{z}; \theta)$ is the probability of obtaining \mathbf{z} given that the parameters were in state θ . With a priori assumptions concerning the probability distribution for the parameters, the most likely set of parameters can be obtained through solving for θ in

$$\frac{\partial p(\theta; \mathbf{z})}{\partial \theta_i} = 0 = \frac{\partial p(\mathbf{z}; \theta)}{\partial \theta_i}, \quad (2)$$

where $p(\theta; \mathbf{z})$ is the probability that the parameters were in state θ given the data was observed to be \mathbf{z} .

A closed form analytical expression for the form of the cross-correlation function for water column returns enables the model correlation matrix, \mathbf{R} , to be computed as a function of the unknown parameters (including velocity). This \mathbf{R} matrix may then be used along with the data correlation matrix, $\mathbf{z}_i \mathbf{z}_j^*$, to form the probability function. The values of the unknown parameters may then be varied in an iterative search for the maximum of the probability function, which is equivalent to solving the set of simultaneous equations represented by equation (2). The expansion involves infinite sums over half-integer spherical Bessel functions and Legendre polynomials. In practice the sums may be truncated after several terms to obtain an adequate approximation.

To simplify the calculation, the natural logarithm is applied to equation (1) and, as a minimum is desired, the equation is multiplied by -1 so that the function of unknown parameters, g , becomes,

$$g(V_x, V_y, V_z, SNR_{\tau=0}, SNR_{\tau=\tau_c}, \alpha, \beta, W, a) = -\ln p(\mathbf{z}; \theta) =$$

$$-\ln \frac{1}{\pi^n} + \ln |\mathbf{R}_{model}| + \text{Trace}(\mathbf{R}_{data} \mathbf{R}_{model}^{-1}) \quad (3)$$

The first term can be ignored in the calculation as it is an offset curve. In one presently preferred system 200, the set of unknown parameters are as follows:

v_x = the water velocity along the x-axis;
 v_y = the water velocity along the y-axis;
 v_z = the water velocity along the z-axis;
 $SNR_{\tau=0}$ = the signal-to-noise ratio at lag $\tau=0$;
 $SNR_{\tau=\tau_c}$ = the signal-to-noise ratio at lag $\tau=\tau_c$;
 α = effective relative angle of the azimuth (Figure 5);
 β = effective relative seabed tilt from the vertical;
 W = width parameter of angular scattering function; and
 a = wing parameter of angular scattering function.

Thus, in the maximum likelihood method, the unknown parameters are varied to minimize the function, g , and thereby maximize the probability of observing the received data in a specified parameter state.

IV. MODEL CORRELATION MATRIX

The model correlation matrix R_{model} , or just R in this section, can be calculated using a closed form expression for the spacial correlation function R . As water volume returns and bottom returns require somewhat different processing due to seabed tilt and seabed roughness issues, the following discussion presents an expression for the spacial correlation function used with water volume returns followed by several expressions for the spacial correlation function used with bottom returns. The expressions used with bottom returns differ as follows: the first expression assumes the seabed exhibits a Lambertian scattering function, i.e., $\cos(\theta)$; the second expression assumes the seabed exhibits a Kirchhoff approximation scattering function, i.e., $\sigma(\theta)$; and the third expression is a heuristic which much simplifies the calculations for R .

In the presently preferred embodiment, the structure of R is determined in the following way. The inbound pressure data points in time are numbered 1-8 for data at time $t=0$ for receivers 1-8, respectively, and 9-16 for data at time $t=\tau_c$ for receivers 1-8, respectively; then 17-24 for data at time $t=\Delta t$ (where Δt is the sample interval) and 25-32 for data at time $t=\tau_c + \Delta t$, again for receivers 1-8, respectively, and so forth. A very large correlation matrix of size $8m \times 8m$ is then generated for a system comprising 8 receivers and collecting " m " data points in time at a sampling interval of Δt . The value for " m " depends on a variety of factors which may include altitude, water profiling bin resolution, and number of code elements transmitted. For simplicity, it will be assumed that the sampling interval Δt is commensurate with the system bandwidth so that each sample in time is independent. It is then easily seen that the $8m \times 8m$ large matrix is really a block diagonal matrix with 16×16 submatrices down the main diagonal and zeros elsewhere. That is, data points 1-8 are correlated among themselves (spatial correlation function at 0 timeshift) and they are correlated with entries 9-16 (spatial correlation function at τ_c timeshift) but they are uncorrelated with all other data points. Likewise, entries 17-32 constitute a 16×16 submatrix, and so forth. Because the monopulse approach typically ensconces all the scatterers in the beam pattern simultaneously, the nature of each 16×16 submatrix along the main diagonal is the same, i.e., each 16×16 submatrix along the main diagonal of the large $8m \times 8m$ matrix represents the spatial correlation function evolving in time. However, an advantage of the beam filled monopulse method is that the spatial correlation function becomes stationary, i.e., not a function of time. Thus, only an individual 16×16 submatrix need be considered for R . The spatial correlation function at zero time shift is contained in the upper left 8×8 and lower right 8×8 portion of R . The spatial correlation function at τ_c time shift is contained in the upper right 8×8 and lower left 8×8 portion of R . R is of course, Hermitian.

As is well-known in the transducer technology, the beam pattern, $W(\theta)$, where θ is the angle of measured energy away from the axis of wave propagation, can be represented as a finite series of Legendre polynomials with coefficients b_n , which thus allows the spacial correlation function to be a function of sum of integrals which involve the n^{th} term of the beam pattern. (One description of Legendre polynomials is provided in Mathematical Methods for Physicists by George Arfen, Academic Press, New York, pp. 534-608.) Calling each of these integrals R_n ,

$$\begin{aligned}
 R_n = e^{i\psi} \left[\frac{2\pi}{\delta} \right]^{1/2} \sum_{k=0}^{\infty} (1/2+k) i^{-k} J_{1/2+k}(\delta) P_k(\cos \epsilon) \\
 \times \int_0^{\pi/2} d\theta \sin \theta P_n(\cos \theta) P_k(\cos \theta)
 \end{aligned} \quad (4)$$

where J is a Bessel function and P is a Legendre polynomial. Thus, the spacial correlation function is the sum of integrals as follows:

$$R = \sum_{n=0}^{\infty} b_n R_n \quad (5)$$

where each b_n is a Legendre polynomial coefficient, and where

$\psi = k[v_x(a_4 - a_1) + v_y(a_5 - a_2) + v_z(a_6 - a_3)]/c$, the expression for a correction to the phase corresponding to path differences of order v/c , where v is water velocity and c is the speed of sound in water

$k = 2\pi/\lambda$

c = speed of sound in water

λ = wavelength of the propagated sound wave

and further where the first and second receivers are located in the sensor frame at $(A_1, A_2, 0)$ and $(A_4, A_5, 0)$ respectively. Because the sensor can change attitude between the time of transmission and the time of reception, a rotation matrix must be applied to obtain the receiver locations appropriate in the coordinate system of the sensor at the time of transmission:

$$a_4 - a_1 = \cos\alpha \cdot \cos\beta \cdot [A_4 - A_1] \cos\gamma - (A_5 - A_2) \sin\gamma - \sin\alpha [(A_4 - A_1) \sin\gamma + (A_5 - A_2) \cos\gamma]$$

$$a_5 - a_2 = \sin\alpha \cdot \cos\beta [(A_4 - A_1) \cos\gamma - (A_5 - A_2) \sin\gamma] + \cos\alpha [(A_4 - A_1) \sin\gamma + (A_5 - A_2) \cos\gamma]$$

$$a_6 - a_3 = -\sin\beta [(A_4 - A_1) \cos\gamma - (A_5 - A_2) \sin\gamma]$$

$$\alpha = \tan^{-1} (-\sin\gamma \cdot \cos\beta / \cos\gamma)$$

$$\delta = k[(2\tau v_z + a_6 - a_3)^2 + (2\tau v_x + a_4 - a_1)^2 + (2\tau v_y + a_5 - a_2)^2]^{1/2} \quad (6)$$

$$\tan\epsilon = \frac{[(2\tau v_x + a_4 - a_1)^2 + (2\tau v_y + a_5 - a_2)^2]^{1/2}}{2\tau v_z + a_6 - a_3} \quad (7)$$

Unfortunately, the Legendre polynomials are orthogonal on the interval $(-\pi/2, \pi/2)$, and not the integration interval of $(0, \pi/2)$. However, after some further mathematical work on the equation it can be shown that the closed form expression for R_n is as follows:

$$R_n = e^{i\psi} \left\{ \left[\frac{2\pi}{\delta} \right]^{1/2} (1/2 + n) i^{-n} J_{1/2+n}(\delta) P_n(\cos\epsilon) \frac{1}{2n+1} + \right. \\ \left. \left[\frac{2\pi}{\delta} \right]^{1/2} \sum_{\substack{k=1 \\ \text{odd}}}^n (1/2 + k) i^{-k} J_{1/2+k}(\delta) \right. \\ \times P_k(\cos\epsilon) (-1)^{(n-k-1)/2} \frac{(n-1)!! k!!}{n!! (k-1)!! [k(k+1) - n(n+1)]} \text{ if } n \text{ is even} \\ \left. \left[\frac{2\pi}{\delta} \right]^{1/2} \sum_{\substack{k=0 \\ \text{even}}}^n (1/2 + k) i^{-k} J_{1/2+k}(\delta) \right. \\ \times P_k(\cos\epsilon) (-1)^{(n-k-1)/2} \frac{(k-1)!! n!!}{k!! (n-1)!! [n(n+1) - k(k+1)]} \text{ if } n \text{ is odd} \} \quad (8)$$

where

$$\delta = k[(2\tau v_z + a_6 - a_3)^2 + (2\tau v_x + a_4 - a_1)^2 + (2\tau v_y + a_5 - a_2)^2]^{1/2} \quad (9)$$

$$\cos \epsilon = \frac{2\tau v_z + a_6 - a_3}{(\delta/k)} \quad (10)$$

Depending on the parity of the beam pattern term being considered, i.e., n is even or odd, only one of the sums in equation (8) is to be used. δ is the total distance away from the bistatic point in all three dimensions and ϵ is a phase angle describing the relative contribution of vertical and horizontal displacement. In practice, the sums in equation (8) may be truncated after a few terms to obtain an adequate approximation to R_n . Equation (5) is then used to sum over the coefficients of the beam pattern to obtain the final, total correlation value.

A spacial correlation function to model bottom returns coming from a seabed is also important, however such a function should incorporate the existence of a tilted seabed as, for example, shown in Figure 5. A four variable closed form expression is provided below:

$$R = \frac{e^{i\psi}}{2 \sum_{l=0}^L b_l I_{l0}^0 P_l(\cos \beta)} \times \left[\begin{aligned} & (2\pi/r)^{1/2} \sum_{l=0}^L b_l [P_l(\cos \beta) \sum_{j=0}^{\infty} i^{-j} I_{lj}^0 J_{j+1/2}(r) P_j(\cos \eta) + \\ & 2 \sum_{m=1}^l P_l^m(\cos \beta) (-1)^m \cos[m(\phi_0 - \alpha)] \sum_{j=m}^{\infty} i^{-j} I_{lj}^m J_{j+1/2}(r) P_j^m(\cos \eta)] \end{aligned} \right] \quad (11)$$

where

Variable	Significance
r	$(2\pi/\lambda) \times$ the total three axis distance the lag is from the bistatic point ($2\tau v_x, 2\tau v_y, 2\tau v_z$)
$\tan \eta$	the ratio of the horizontal distance away from the bistatic point to the negative of the vertical lag away from the bistatic point (defined in the seabed frame)
β	the nadir tilt angle of the seabed
$\phi_0 - \alpha$	the azimuthal angle corresponding to the ratio of distance away in the y lag to x lag indexed off of the azimuthal angle in which the seabed is tilted

and where ring geometry coefficients are defined as:

$$I_{lj}^m = (1/2 + j) \frac{(l-m)! (j-m)!}{(l+m)! (j+m)!} \int_0^\pi \sin \theta \cos \theta P_l^m(\cos \theta) P_j^m(\cos \theta) d\theta \quad (12)$$

In equation (12), where l and j are dummy indices which are being summed over, it is assumed that the seabed scattering follows a Lambertian law (i.e., intensity is proportional to $\cos \theta$) and that the function includes the combined effect of a series of rings from θ_1 to θ_2 . If the angular scattering law of the seabed is not $\cos \theta$, but $\sigma(\theta)$ instead, then $\sigma(\theta)$ must be substituted for $\cos \theta$ in equation (12). The expression of equation (11) may be too complicated for many real-time applications so a two variable approximation has been derived as follows:

$$R = \frac{(2\pi/r)^{1/2} e^{i\psi}}{2 \sum_{l=0}^L b_l I_{l0}^0} \times \left[\sum_{l=0}^L b_l \sum_{j=0}^{\infty} i^{-j} I_{lj}^0 J_{j+1/2}(r) P_j(\cos \eta) \right] \quad (12.1)$$

Unfortunately, under certain seabed roughness conditions the scattering function may not follow a Lambertian law.

This may be true if the scattering function of the seabed is strongly dependent on the angle of the beam, being strongest at small angles near nadir. Thus, some alternative to the Lambertian function may be required to more accurately predict acoustic scattering on a seabed.

The Kirchhoff approximation assumes that the seabed surface is slowly varying so that the radius of curvature is much greater than a wavelength. Some researchers, including Clay, C.S. and Medwin, H. 1977, Acoustical Oceanography, John Wiley and Sons Publishing, have noted that the Kirchhoff approximation works reasonably well under a variety of realistic situations provided the incident angles do not approach grazing angles. Fortunately, for almost any conceivable correlation sonar geometry, most of the sound is closer to normal incidence than grazing incidence.

The expression for the backscatter cross section per unit area per unit solid angle for the diffuse scatter field under the Kirchhoff approximation can be derived, (following the development by Jackson, et al. in "Application of the Composite Roughness Model to High-Frequency Bottom Backscattering", J. Acoust. Soc. Am. 79 (5), May 1986) and is defined as follows:

$$\sigma(\theta) = \frac{k^2 R_{\text{ro}}^2}{2\pi^2 \cos^2 \theta} \int_{-\infty}^{\infty} dx \int_{-\infty}^{\infty} dy \exp[2ik \sin(\theta) x] \times \exp[-2k^2 \cos^2(\theta) D(r)] \quad (13)$$

where the structure function $D(r)$ is used instead of the correlation function and the structure function is defined as $D(r) = 2[B(0) - B(r)]$ where $B(r)$ is the spatial autocorrelation function of the seabed and R_{ro} is a reflection coefficient.

Most data on bottom roughness are derived from bathymetry and have a resolution of 100 meters or larger. Two-dimensional roughness spectra with centimeter scale resolution have been measured by Akal, T. and Hovem, J., 1978, "Two-dimensional space series analysis for seafloor roughness," Marine Geotechnol. 3, 171-182. Others in the literature have provided one-dimensional roughness spectra with centimeter-scale resolution. The data from coarse and fine seabed roughness measurements agree in having power-law roughness spectra. Therefore, this model assumes that the two-dimensional seabed roughness statistics are Gaussian and isotropic with a spatial power spectrum of the form

$$\Phi(k) = \beta k^{-\gamma} \quad (14)$$

where k is a two-dimensional wave vector having a magnitude equal to the wavenumber, k , and β and γ parameters describe a particular power spectrum of the seabed. The β and γ used in equation (14) are different and should not be confused with the β and γ angles used earlier. The noted high resolution data has the following approximate range for γ : $3 < \gamma < 3.5$.

After relating the structure function to the spatial power spectrum and the substitution of $\alpha = (\gamma/2) - 1$ is made then

$$D(r) = C_h^2 r^{2\alpha} \quad (15)$$

where

$$C_h^2 = \frac{2\pi\beta 2^{-2\alpha} \Gamma(2-\alpha)}{\alpha(1-\alpha) \Gamma(1-\alpha)} \quad (15.1)$$

$$\alpha = (\gamma/2) - 1$$

where C_h is a structure constant, also sometimes called a structure function parameter, and $\Gamma(x)$ is the gamma function. Again a here should not be confused with the α angle used earlier. The final backscatter equation can be derived by incorporating the structure function given in equation (15) into equation (13) and simplifying to yield

$$\sigma(\theta) = \frac{R_{fc}^2}{4\pi \sin^2(\theta) \cos^2(\theta)} \int_0^\infty du u J_c(u) \exp(-qu^{2\alpha}) \quad (16)$$

where

$$q = 2^{(1-2\alpha)} k^{(2-2\alpha)} \cos^2(\theta) C_h^2 \sin^{-2\alpha}(\theta) \quad (17)$$

where q is an arbitrary variable chosen to simplify the equation. Equations (16) and (17) can be numerically computed to yield the backscatter cross section per unit area per solid angle as a function of angle θ .

Although the Kirchhoff approximation appears to provide an accurate estimate of scattering, in investigating the various scattering curves corresponding to different degrees of seabed roughness a heuristic for the spacial correlation function R was discovered. The heuristic is used as an alternative expression when there are certain real-time constraints in the processing. The heuristic is a general function for band shapes as can be found, for example, in Spectral Analysis by James Blackburn. The magnitude of the complex R , the spacial correlation function, expression is as follows:

$$R = \frac{R_{peak}}{\{1 + (2^a - 1)[2(X - X_0)/W]^2\}^{1/a^2}} \quad (18)$$

where X_0 is the center of the curve, W is the width parameter defined as twice the distance from the center to the 1/2 curve height point and a is a wing parameter specifying the extent of the curve wing. R_{peak} is either initially set high to .9 or estimated from the amplitude pressure data of the seabed return relative to the noise floor and a is set to 1/2. Note that if a is set to 0, the curve is a Gaussian, and if a is set to 1, the curve is a Lorentzian. In addition to the magnitude of the complex R shown in equation (18), the heuristic includes a phase angle factor which is applied to the magnitude to generate the complete heuristic complex R . The phase angle factor is as follows:

$$e^{i(\psi + \delta \cos \epsilon)} \text{ or } e^{i(\psi - r \cos \eta)}$$

V. OPERATION OF THE CORRELATION SONAR

Maximum likelihood processing specific to the presently preferred acoustic correlation current profiler (correlation sonar) embodiment of the correlation sonar system is presented by general reference to Figures 11 and 12. In the Figures, function names used in the preferred software appear to the right of their corresponding state. Software for the present system is written in the FORTRAN language. The software described herein, particularly the portion listed in the attached Microfiche Appendix, was translated from source code to machine-readable object code using the NDP FORTRAN Version 4.0b compiler licensed from Microway. Nonetheless, one skilled in the technology will recognize that the steps in the accompanying flow diagrams can be implemented by using any of a number of different computer languages and language translators.

Now referring more specifically to Figure 11, there is shown the correlation sonar software, generally indicated at 250, that is stored in the memory (not shown) of the host computer 214 (Figure 10), and which controls signal generation and echo sampling, and conducts analysis of the sampled data to obtain velocity measurements. Beginning at power on, the correlation sonar enters a start state 252 and continues to state 254 to initialize the software by creating data structures and reading parameters from files on the disk 244, and at state 256 data is stored in registers to initialize the hardware.

At present, one of the software initialization parameters specified by the user is "bottom track mode". If the parameter is true a bottom track has been requested, and the execution flow proceeds down the right portion of the flow diagram; otherwise, a water profile has been requested, and the execution flow proceeds down the left portion of the flow diagram. Of course, one skilled in the technology will comprehend that the modes are for programming convenience and that the functionality of both modes could be combined so that bottom tracking and current profiling occur "together". In that way, the earth reference velocity of the water currents could be completely obtained within the correlation sonar 200 by subtracting the bottom tracking, or vessel, velocity from the current velocities.

As the right and left portions of the flow diagram in Figure 11 overlap in most functions, only the left side will be discussed herein on a state-by-state basis. Thus, assuming that the user has specified measurements for a water profile, such as the example shown in Figure 8, the correlation sonar enters state 260 to select a specific code that is used to control the timing generator 232 (Figure 232) and, hence, generate a coded pulse from the transmitter transducer 208.

The sequence data indicative of the echo signal is received from the demodulators 222 (Figure 10) by the CPU 228, and forwarded to the host computer 214. The correlation sonar 200 then enters state 264 to unpack the sequence data. Specifically, the sine and cosine binary data for two receiver transducers 210 and 1 byte of amplitude data, sampled at a lesser rate, for each transducer 210 are all packed into the digital sequence. Therefore, the different data and data from different sources is extracted at state 264. Proceeding to state 266, the cross-correlation matrix, $R(0)$ for a time lag of 0 is created for all eight of the receiving transducers 210 (Figures 9 and 10), thus creating an 8 x 8 matrix, wherein each row and column corresponds to a receiving transducer. Subsequently, at state 268, the cross-correlation matrix, $R(\tau)$ for a time lag of τ_c is created as another 8 x 8 matrix. Then, a "seed" is generated for the maximum likelihood signal processing at state 270. Here, accuracy is not the consideration so much as providing an initial guess for the water velocity unknowns, v_x , v_y , and v_z . This is accomplished by using a 3 x 3 matched filter approach on the $R(\tau)$ matrix to average the contents of every nine neighborhood amplitude correlation coefficients. A first moment technique is then used and the results are divided by 2τ to obtain an initial estimate of v_x and v_y . The velocity v_z could be set to zero. However, more preferably, the phase shift of the highest correlation coefficient can be used to estimate v_z .

Two transducer pairs, one up from the origin and one to the right of the origin, are used to index the $R(0)$ matrix so as to estimate effective sensor tilt or seabed angles α and β . The phase shifts are indicative of the direction of sound propagation in two dimensions.

The initial SNR_0 estimate can be obtained from the amplitude pressure data relation to the noise floor, or it can be set to a high value, say 10, arbitrarily. The SNR_τ estimate can be determined by selecting the highest correlation coefficient from the $R(\tau)$ matrix and then using the following equation:

$$\frac{1}{\text{magnitude}(p)} = 1 + \frac{1}{SNR} \quad (19)$$

After setting the above-noted estimated parameters, the correlation sonar 200 enters state 272 to handle maximum likelihood (ML) signal processing. The inputs to state 272 can be categorized into three groups, group one contains the following inputs: α , β , SNR_0 , SNR_τ , v_x , v_y , and v_z ; (w and a are also included for bottom tracking), which were calculated at state 270. Group two contains the changes in the group one parameters. Initially, these values are determined based upon reasonable guesses. Group three contains cross-correlation matrices $R(0)$ and $R(\tau)$. The outputs of the ML state 272 are the new group one parameters. The ML processing is executed on the host computer 214 (Figure 10) after either receiving the raw data and forming the correlation matrices or receiving the cross-correlation matrices directly from the DSP 230 of the electronics assembly 204. The function of state 272 will be discussed hereinbelow with reference to Figure 12.

Continuing to refer to Figure 11, after the completion of the ML signal processing (state 272) the correlation sonar 200 moves to state 274 to store the outputs: α , β , SNR_0 , SNR_τ , v_x , v_y , and v_z , (and w and a for bottom tracking), to the data storage device 244 (Figure 10). Also, $-\ln(P)$ is stored which is indicative of a goodness of fit. Then, at state 276 a coded pulse is selected, which is not necessarily the default code as was selected at state 260. In fact, the code is selected according to the relative measured velocity of the water and in the case of bottom tracking, the currently estimated altitude to the seabed.

The pseudorandom codes are selected primarily based on the length and correlation lag time. Length is important for the following two tracking criteria:

- (i) for water tracking because it determines the spatial resolution of each water bin. Long codes will produce coarse resolution in the profiling of current velocity. They, however, have the advantage of depositing the most amount of energy into the water and permit maximum range. Shorter codes allow better resolution (up to a point where the beamwidth geometry begins to dominate the bin profile resolution), but they do not place as much energy into the water.
- (ii) for bottom tracking the code length is chosen to be long enough to typically encompass all the scatterers within the beam pattern on the seabed and allow sufficient time to perform the necessary cross-correlations.

Lag time, τ_c , is important because the location of the peak is approximately given by $2\tau_c$ velocity. Thus, τ_c is chosen based on velocity such that the peak location will remain on the configured array of receivers, otherwise accuracy in the estimated velocity is compromised. However, if τ_c is selected to be too low, thereby virtually guaranteeing the peak is on the array for even high velocity, precision in the estimate tends to be lost. These two considerations must be

constantly monitored and traded-off to arrive at a proper selection of lag time.

The ping for the selected code is generated at state 278 in the same manner as was described with respect to state 262. In receiving the echo signal for current profiling, the echo return signal is range gated (or, equivalently, time gated) by looping over the states 280-294, wherein state 280 is a counter state for incrementing the bin, or cell, number. The bin number is calculated according to the length of the pulse and the velocity resolution specified by the user. The loop is finally exited at state 294 when a test of the bin counter indicates that all bins for this ping have been processed. It should be noted that preferably a weighing function based on depth is used to determine the number of profile bins. For example, the program DETPRO in the Microfiche Appendix will provide a weighted bin profile. Velocity measurements based on a new ping are initiated again at state 276, and they continue until the correlation sonar 200 is either reset or powered down.

Returning, in the discussion of Figure 11, to the right portion of the flow diagram which relates to the bottom tracking mode of operation, most states have been labeled with the same number as the left portion (current profiling mode) followed by prime (') to indicate identical or similar functionality. However, states not shown in the left portion include states 296, 298 and 300. Specifically, state 296 is entered after an initial ping (state 262') to find the seabed. If the seabed is not found, a new code is selected and ping generated until it is found. This state is accomplished using a matched filter approach which is a modified version of the process disclosed in the common assignee's previously cited patent. The loop from states 276'-292' is continuously executed unless the seabed is not found, e.g., the vessel passes over a canyon. In that case, the correlation sonar 200 moves from state 298 to state 300 to report the loss of tracking and a the bottom track initialization (states 260', 262', 296) is again carried out.

One presently preferred function for maximum likelihood (ML) signal processing is shown diagrammatically in Figure 12. Note that parameters characterizing seabed roughness, e.g., the width parameter, W, and the wing parameter, -a, both of which were discussed above, are not shown in Figure 12, but could be readily incorporated therein by one who is skilled in the relevant technology.

Generally, the function uses a dual fit approach, namely, three parameters for water profiling or five parameters for bottom tracking are fit, then the remaining four parameters are fit. In particular, the effective tilt angles, α and β , and the signal-to-noise ratio at time lag 0, SNR_0 naturally reside in the lag 0 correlation space. Likewise, SNR_τ , and the water velocities, v_x , v_y , and v_z , naturally reside in the lag τ correlation space.

The ML function, used in states 272, 290, 272', 290' (Figure 11), is entered by the correlation sonar 200 (Figure 10) at start state 310. Whether the first or second parameter pass is being calculated depends on the FITFLG (fit flag) which is initially set to true at state 312 to indicate α , β and SNR_0 will be fit. As the multi-variate, non-linear programming optimization relies on the well-known simplex algorithm, a four (six for bottom tracking) vertex polyhedron is formed by evaluating the negative of the natural logarithm of the probability function, g_1 , at the model parameters and at each parameter varied by an offset as follows (brackets denote additional parameters required for bottom tracking):

$$g_1 (\alpha_0, \beta_0, SNR_0, [w_0, a_0]) \quad (20.1)$$

$$g_1 (\alpha_0, \beta_0 + \Delta\beta_0, SNR_0, [w_0, a_0]) \quad (20.3)$$

$$g_1 (\alpha_0, \beta_0, SNR_0 + \Delta SNR_0, [w_0, a_0]) \quad (20.4)$$

$$g_1 (\alpha_0 + \Delta\alpha, \beta_0, SNR_0, [w_0, a_0]) \quad (20.2)$$

$$g_1 (\alpha_0, \beta_0, SNR_0, [w_0 + \Delta w_0, a_0]) \quad (20.5)$$

$$g_1 (\alpha_0, \beta_0, SNR_0, [w_0, a_0 + \Delta a_0]) \quad (20.6)$$

It is important to note that the offsets are estimated. If the offsets are too large, the simplex method, which iteratively moves along the edges of the polyhedron, may be misled into a local minimum instead of the desired global minimum. On the other hand, if the offsets are too small, the simplex method may take too long to complete because the starting point of the iteration is far from the global optimum and the incremental change at each iteration is so small.

The simplex method in the correlation sonar 200 is presently implemented in a FORTRAN subroutine named

AMOEBAs (since the method "oozes" down the edges of the tetrahedron). The subroutine is based on the simplex method given in "Numerical Recipes, The Art of Scientific Computing" by Press, Flannery, Teukolsky, and Vetterling, specifically described in Section 10.4 entitled "Downhill Simplex Method in Multidimensions"; Press Syndicate of the University of Cambridge. One of the parameters in the subroutine is ITER, the number of iterations to be performed by AMOEBA. At each iteration the unknown parameters α , β , and SNR_0 (and $[w_0, a_0]$ for bottom tracking) are evaluated in g_1 as follows:

$$g_1 = \ln |\det(A_{\text{model}})| + \text{Trace}(A_{\text{data}} A_{\text{model}}^{-1}) \quad (21)$$

where A is an 8×8 matrix equal in structure to $R(0)$. Thus, a user defined maximum number of iterations will prevent an endless iteration over the search space, and a test is made at state 318, to determine whether the maximum number of iterations was exceeded. If so, a report of the status is written to the video display of the host computer 214 (Figure 10) and the ML process completes with incomplete results at state 322.

Otherwise, if the simplex method (state 316) did converge within the predetermined number of iterations, the presumed global optimum for the set of unknown parameters in the first gamma function, g_1 , is stored to system memory at state 324. Then, the FITFLG is set to false, at state 326, to indicate that the second set of unknown parameters will be fit. In this instance, at state 328 the unknown parameters, SNR_t , v_x , v_y , and v_z are fit according to the second gamma function, g_2 , as follows:

$$g_2 = \ln |\det(P_{\text{model}})| + \text{Trace}(P_{\text{data}} P_{\text{model}}^{-1}) \quad (22)$$

A five vertex simplex is created by evaluating g_2 at the five parameter sets defined by varying the offsets, similar to the method employed in state 314 described above. In calculating g_2 , a 16×16 matrix, P (or RHO), is created wherein the matrix can be described as having four 8×8 complex submatrices. The upper left submatrix is $R(0)$, the upper right submatrix is $R(\tau)$, the lower left submatrix is the complex conjugate of $R(\tau)$, and the lower right submatrix is $R(0)$. This special matrix structure allows a fast matrix inversion.

Again, the simplex method is applied to search a multi-variate parameter space, this time a five parameter space at state 330. If the maximum number of iterations are determined to have been exceeded at state 332, then a report is made (state 334) and the correlation sonar 200 exits the ML procedure at state 336. Alternatively, continuing from state 332 to state 338 a solution has been found and the control flow continues to return the seven (nine for bottom tracking) parameters in system memory. The ML process then returns control flow back to the correlation sonar top-level flow as shown diagrammatically in Figure 11.

Claims

1. A correlation sonar system (200) having a transmitting transducer (208) for emitting acoustic energy onto a reflecting surface, a pulse generation means for generating a single pulse (110) of electrical energy to the transmitting transducer, a plurality of receiving transducers (210) for receiving a pulse echo (110') from the reflecting surface, a plurality of demodulators (222), each demodulator connected to one of the receiving transducers and generating a set of values and maximum likelihood means for estimating velocity using correlated values, characterised by further including:
 - a means (230) for auto-correlating said values for each receiving transducer, and cross-correlating between different receiving transducers, at one or more predetermined time delays less than the pulse width.
2. The system of Claim 1, wherein the pulse comprises a plurality of coded elements.
3. The system of Claim 2, wherein each coded element comprises a plurality of carrier cycles.
4. The system of Claim 3, wherein each coded element is more than two and less than ten carrier cycles.
5. The system of Claim 2, wherein the coded elements are phase encoded.
6. The system of Claim 5, wherein the coded elements are encoded with either of 0 degree and 180 degree phases.

7. The system of Claim 2, wherein the pulse includes sets of non-identical code elements so as to provide zeroes on either side of a preselected autocorrelation peak lag.

8. The system of Claim 1, wherein the pulse has a temporal autocorrelation peak at the predetermined time delay.

9. A correlation sonar system (200) having a means for generating a pulse (110) into a liquid having reflective surfaces, a plurality of transducers (210) for receiving the echo signal (110') created by the pulse contacting the reflective surfaces, and maximum likelihood means for maximizing the probability of a set of preselected parameters, including at least one component of velocity, having sets of correlations indicative of a parameter state, said system characterised by further comprising:

correlation means for forming correlations of the echo signal received by each transducer at a predetermined time lag with the echo signal received by the same transducer at one or more other time lags, and with the echo signals received by the other transducers at one or more of the other time lags, said correlations providing for the spatial relationship of the transducers.

10. The system defined in Claim 9, wherein the correlation means includes means for calculating correlations of the echo signal using a spacial correlation function defined as follows:

$$R = \sum_{n=0}^{\infty} b_n R_n$$

where

b_n is a Legendre polynomial coefficient,

R_n is a spacial correlation function involving the nth term of the beam pattern $W(\theta)$,

$W(\theta)$ is the system beam pattern, and

θ is the angle of measured energy away from the axis of wave propagation.

11. The system defined in Claim 10, wherein the closed form analytical expression for R_n is defined as follows:

$$R_n = e^{i\psi} \left\{ \left[\frac{2\pi}{\delta} \right]^{1/2} (1/2+n) i^{-n} J_{1/2+n}(\delta) P_n(\cos \epsilon) \frac{1}{2n+1} + \right. \\ \left. \left[\frac{2\pi}{\delta} \right]^{1/2} \sum_{\substack{k=1 \\ \text{odd}}}^{\infty} (1/2+k) i^{-k} J_{1/2+k}(\delta) \right. \\ \times P_k(\cos \epsilon) (-1)^{(n+k-1)/2} \frac{(n-1)!! k!!}{n!! (k-1)!! [k(k+1)-n(n+1)]} \text{ if } n \text{ is even} \\ \left. \left[\frac{2\pi}{\delta} \right]^{1/2} \sum_{\substack{k=0 \\ \text{even}}}^{\infty} (1/2+k) i^{-k} J_{1/2+k}(\delta) \right. \right. \\ \left. \times P_k(\cos \epsilon) (-1)^{(n+k-1)/2} \frac{(k-1)!! n!!}{k!! (n-1)!! [n(n+1)-k(k+1)]} \text{ if } n \text{ is odd} \right\}$$

where

n is the nth term of the beam pattern,

$\psi = k[v_x(a_4-a_1)+v_y(a_5-a_2)+v_z(a_6-a_3)]/c$, the expression for a correction to the phase corresponding to path differences of order v/c , where v is water velocity and c is the speed of sound in water,

$\delta = (2\pi/\lambda) \times$ the total three axis distance the lag is from the bistatic point, where λ is the wavelength of the propagated sound wave,

J is a Bessel function,

p is a Legendre polynomial,

ϵ is a phase angle describing the relative contribution of vertical and horizontal displacement, and $k = 2\pi/\lambda$, where λ is the wavelength of the propagated sound wave.

12. The system defined in Claim 9, wherein the closed form analytical expression for the spacial correlation function includes a Lambertian scattering law function.

13. The system defined in Claim 12, wherein the spatial correlation function is defined as follows:

$$R = \frac{e^{i\psi}}{2 \sum_{l=0}^{\infty} b_l I_l^0 P_l(\cos\beta)} \times \left[(2\pi/r)^{1/2} \sum_{l=0}^L b_l [P_l(\cos\beta) \sum_{j=0}^{\infty} i^{-j} I_l^j J_{j-1/2}(r) P_j(\cos\eta) + 2 \sum_{m=1}^l P_l^m(\cos\beta) (-1)^m \cos[m(\phi_0 - \alpha)] \sum_{j=m}^{\infty} i^{-j} I_l^m J_{j-1/2}(r) P_j^m(\cos\eta)] \right]$$

where

$\psi = k[v_x(a_4 - a_1) + v_y(a_5 - a_2) + v_z(a_6 - a_3)]/c$, the expression for a correction to the phase corresponding to path differences of order v/c , where v is water velocity and c is the speed of sound in water,

L is an upper limit to a summation,

b_n is a Legendre polynomial coefficient,

I_l^m ring geometry coefficients defined as follows:

$$I_l^m = (1/2 + j) \frac{(l-m)! (j-m)!}{(l+m)! (j+m)!} \int_0^\pi \sin\theta \cos\theta P_l^m(\cos\theta) P_j^m(\cos\theta) d\theta,$$

where

l is a dummy index which is being summed over,

j is a dummy index being summed over,

m is a dummy index which is being summed over,

P is a Legendre polynomial,

β is the nadir tilt angle of the seabed,

$r = (2\pi/\lambda) \times$ the total three axis distance the lag is from the bistatic point $(2\tau v_x, 2\tau v_y, 2\tau v_z)$, where λ is the wavelength of the propagated sound wave, and

τ is a time shift,

J is a Bessel function,

$\cos\eta$ is the negative of the vertical lag away from the bistatic point,

$\phi_0 - \alpha$ is the azimuthal angle corresponding to the ratio of distance away in the y lag to x lag indexed off of the azimuthal angle in which the seabed is tilted.

14. The system defined in Claim 12, wherein the spatial correlation function is defined as follows:

$$R = \frac{(2\pi/r)^{1/2} e^{i\psi}}{2 \sum_{l=0}^{\infty} b_l I_l^0} \times \left[\sum_{l=0}^{\infty} b_l \sum_{j=0}^{\infty} i^{-j} I_l^j J_{j-1/2}(r) P_j(\cos\eta) \right]$$

where

r is $(2\pi/\lambda) \times$ the total three axis distance the lag is from the bistatic point $(2\tau v_x, 2\tau v_y, 2\tau v_z)$, where λ is the wavelength of the propagated sound wave and

τ is a time shift,
 v_x is the water velocity along the x-axis,
 v_y is the water velocity along the y-axis,
 v_z is the water velocity along the z-axis,

$\psi = k[v_x(a_4 - a_1) + v_y(a_5 - a_2) + v_z(a_6 - a_3)]/c$, the expression for a correction to the phase corresponding to path differences of order v/c , where v is water velocity and c is the speed of sound in water,

L is an upper limit to a summation,

b_n is a Legendre polynomial coefficient,

I_{ij}^m are ring geometry coefficients defined as follows:

$$I_{ij}^m = (1/2 + j) \frac{(1-m)! (j-m)!}{(1+m)! (j+m)!} \int_0^{\pi} \sin \theta \cos \theta P_i^m(\cos \theta) P_j^m(\cos \theta) d\theta$$

where

θ is the angle of measured energy away from the axis of wave propagation,

m is taken to be zero,

l is a dummy index being summed over,

j is a dummy index being summed over,

J is a Bessel function,

P is a Legendre polynomial, and

$\cos \eta$ is the negative of the vertical leg away from the bistatic point.

15. The system defined in Claim 9, wherein the closed form analytical expression for the spacial correlation function includes a Kirchhoff approximation for the scattering law function.

16. The system defined in Claim 15, wherein the spatial correlation function is defined as follows:

$$R = \frac{e^{i\psi}}{2 \sum_{l=0}^L b_l I_{l0}^0 P_l(\cos \beta)} \times \left[(2\pi/r)^{1/2} \sum_{l=0}^L b_l \left[P_l(\cos \beta) \sum_{j=0}^{\infty} i^{-j} I_{lj}^0 J_{j+1/2}(r) P_j(\cos \eta) + 2 \sum_{n=1}^l P_l^m(\cos \beta) (-1)^n \cos[m(\phi_0 - \alpha)] \sum_{j=n}^{\infty} i^{-j} I_{lj}^m J_{j+1/2}(r) P_j^m(\cos \eta) \right] \right]$$

where

I_{ij}^m are ring geometry coefficients defined as follows:

$$I_{ij}^m = (1/2 + j) \frac{(1-m)! (j-m)!}{(1+m)! (j+m)!} \int_0^{\pi} \sin \theta \cos \theta P_i^m(\cos \theta) P_j^m(\cos \theta) d\theta$$

where

$$\sigma(\theta) = \frac{R_{fo}^2}{4\pi \sin^2(\theta) \cos^2(\theta)} \int_0^\infty du u J_0(u) \exp(-qu^{2\alpha})$$

θ is the angle of measured energy away from the axis of wave propagation.

R_{fo} is a reflection coefficient,

u is a variable over which the integral is taken,

J is a Bessel function,

$$q = 2^{(1-2\alpha)} k^{(2-2\alpha)} \cos^2(\theta) C_h^2 \sin^{-2\alpha}(\theta).$$

Where

q is an arbitrary variable chosen to simplify the equation

$k = 2\pi/\lambda$

λ is the wavelength of the propagated sound wave

C_h is a structure constant, also sometimes called a structure function parameter, and

α is the effective relative angle of the azimuth.

17. The system defined in Claim 9, wherein the closed form analytical expression for the spacial correlation function comprises a general function for band shapes.

18. The system defined in Claim 17, wherein the magnitude of the spatial correlation function is defined as follows:

$$R = \frac{R_{peak}}{\{1 + (2^{a^2} - 1)[2(X - X_0)/W]^2\}^{1/a^2}}$$

where

R_{peak} is the peak spatial correlation,

a is a wing parameter specifying the extent of the curve wing,

X is a value on the curve,

X_0 is the center of the curve, and

W is the width parameter of an angular scattering function defined as twice the distance from the center to the 1/2 curve height point.

19. A method for measuring velocities using a correlation sonar system having a transmitting transducer (208) and a plurality of receiving transducers (210), the method comprising the steps of transmitting a pulse of energy (110) in the direction of a reflective surface, and receiving the pulse energy echo (110') at each receiving transducer as a set of received values, the method further comprising maximum likelihood processing for estimating velocity using correlated values, characterised by:

calculating correlation values from the received values associated with multiple ones of the receiving transducers;

providing initial estimates of a set of unknown parameters; and

maximum likelihood processing the correlation values and initial estimates of parameters to maximize the probability of the system having a specific set of parameters given the correlation values.

20. The method of Claim 19, additionally comprising the step of selecting a code for coding the pulse energy.

21. The method of Claim 20, wherein the code is selected depending on relative measured velocity.

22. The method of Claim 20, wherein the code is selected depending on distance to the reflective surface.
23. The method of Claim 19, wherein the energy is directed toward a plurality of reflective surfaces and the steps are repeated until a specific reflective surface is located.
24. The method of Claim 23, wherein the location of the specific reflective surface is by use of a matched filter.
25. The method of Claim 19, wherein the set of unknown parameters includes a component of velocity.
26. The method of Claim 19, wherein the maximum likelihood processing step includes a simplex algorithm.
27. The method of Claim 19, wherein the maximum likelihood processing step includes evaluating the natural logarithm of the probability function at the initial estimate of parameters and at each parameter varied by an offset.
28. The method of Claim 19, wherein the received values and correlation values are complex numbers.

Patentansprüche

1. Korrelationssonarsystem (200) mit einem sendenden Wandler (209) zum Aussenden akustischer Energie auf eine reflektierende Oberfläche zu, einer Impulserzeugungseinrichtung zum Erzeugen eines einzelnen Impulses (110) aus elektrischer Energie zu dem sendenden Wandler, einer Vielzahl von empfangenden Wandlern (210) zum Empfangen eines Impulsechos (110') von der reflektierenden Oberfläche, einer Vielzahl von Demodulatoren (222), wobei jeder Demodulator mit einem der empfangenden Wandler verbunden ist und einen Satz von Werten erzeugt, und einer Maximumwahrscheinlichkeitseinrichtung zum Schätzen der Geschwindigkeit unter Verwendung korrelierter Werte, gekennzeichnet ferner durch das Einschließen einer Einrichtung (230) zum Autokorrelieren der Werte für jeden empfangenden Wandler und Kreuzkorrelieren zwischen verschiedenen empfangenden Wandlern mit einer oder mehreren vorbestimmten Zeitverzögerungen, die kürzer als die Impulsdauer sind.
2. System nach Anspruch 1, wobei der Impuls eine Vielzahl codierter Elemente aufweist.
3. System nach Anspruch 2, wobei jedes codierte Element eine Vielzahl von Trägerzyklen aufweist.
4. System nach Anspruch 3, wobei jedes codierte Element mehr als zwei und weniger als zehn Trägerzyklen aufweist.
5. System nach Anspruch 2, wobei die codierten Elemente phasencodiert sind.
6. System nach Anspruch 5, wobei die codierten Elemente mit jeweils 0-Grad- und 180-Grad-Phasen codiert sind.
7. System nach Anspruch 2, wobei der Impuls Sätze nichtidentischer Codeelemente umfaßt, so daß Nullen an jeder Seite einer vorgewählten Autokorrelationsspitzenverzögerung vorgesehen werden.
8. System nach Anspruch 1, wobei der Impuls eine zeitweilige Autokorrelationsspitze bei der vorbestimmten Zeitverzögerung aufweist.
9. Korrelationssonarsystem (200) mit einer Einrichtung zum Erzeugen eines Impulses (110) in eine Flüssigkeit mit reflektierenden Oberflächen, einer Vielzahl von Wandlern (210) zum Empfangen des Echosignals (110'), das durch den Impuls erzeugt wird, der auf die reflektierenden Oberflächen trifft, und mit einer Maximumwahrscheinlichkeitseinrichtung zum Maximieren der Wahrscheinlichkeit eines Satzes vorgewählter Parameter, einschließlich zumindest einer Geschwindigkeitskomponente, mit Sätzen von Korrelationen, die einen Parameterzustand zeigen, wobei das System ferner gekennzeichnet ist durch das Aufweisen einer Korrelationseinrichtung zum Ausbilden von Korrelationen des Echosignals, das durch jeden Wandler mit einer vorbestimmten Zeitverzögerung empfangen wird, wobei das Echosignal durch den gleichen Wandler zu einer oder mehreren anderen Zeitverzögerungen empfangen wird und wobei die Echosignale durch die anderen Wandler mit einer oder mehreren der anderen Zeitverzögerungen empfangen werden, wobei die Korrelationen die räumliche Beziehung der Wandler bereitstellen.
10. System nach Anspruch 9, wobei die Korrelationseinrichtung eine Einrichtung zum Berechnen von Korrelationen des Echosignals unter Verwendung einer räumlichen Korrelationsfunktion umfaßt, die definiert ist, wie folgt:

$$R = \sum_{n=0}^{n_{\max}} b_n R_n$$

5

wobei

- b_n ein Legendrepolynom-Koeffizient ist,
 R_n eine räumliche Korrelationsfunktion ist, die den n-ten Term des Strahlmodells $W(\theta)$ enthält,
 $W(\theta)$ das Systemstrahlmodell ist, und
 θ der Winkel der gemessenen Energie von der Achse der Wellenausbreitung weg ist.

10

11. System nach Anspruch 10, wobei der Ausdruck für R_n in der geschlossenen analytischen Form definiert ist, wie folgt:

15

20

25

30

$$\begin{aligned}
 R_n = & e^{i\psi} \left[\left(\frac{2\pi}{\delta} \right)^{1/2} (1/2+n) i^{-n} J_{1/2+n}(\delta) P_n(\cos \epsilon) \frac{1}{2n+1} + \right. \\
 & \left[\left(\frac{2\pi}{\delta} \right)^{1/2} \sum_{k=1}^n (1/2+k) i^{-k} J_{1/2+k}(\delta) \right. \\
 & \times P_k(\cos \epsilon) (-1)^{(n+k-1)/2} \frac{(n-1)!! k!!}{n!! (k-1)!! [k(k+1)-n(n+1)]} \quad \left. \begin{array}{l} \text{falls } n \\ \text{gerade ist} \end{array} \right. \\
 & \left. \left[\left(\frac{2\pi}{\delta} \right)^{1/2} \sum_{k=0}^n (1/2+k) i^{-k} J_{1/2+k}(\delta) \right. \right. \\
 & \times P_k(\cos \epsilon) (-1)^{(n+k-1)/2} \frac{(k-1)!! n!!}{k!! (n-1)!! [n(n+1)-k(k+1)]} \quad \left. \begin{array}{l} \text{falls } n \\ \text{ungerade} \\ \text{ist} \end{array} \right] \quad \left. \vphantom{\sum_{k=0}^n} \right\}
 \end{aligned}$$

wobei

35

40

45

- n der n-te Term des Strahlmodells ist,
 $\psi = k[v_x(a_4-a_1)+v_y(a_5-a_2)+v_z(a_6-a_3)]/c$ der Ausdruck für eine Korrektur hinsichtlich der Phase ist, die zu Phasendifferenzen der Größenordnung v/c gehört, wobei v die Wassergeschwindigkeit ist und c die Geschwindigkeit des Schalls in Wasser ist,
 $\delta = (2\pi/\lambda) \times$ die gesamte Dreiaachsenstrecke die Verzögerung vom bistatischen Punkt ist, wobei λ die Wellenlänge der sich ausbreitenden Schallwelle ist,
 J eine Besselfunktion ist,
 p ein Legendrepolynom ist,
 ϵ ein Phasenwinkel ist, der den relativen Beitrag einer vertikalen und horizontalen Versetzung beschreibt, und
 $k = 2\pi/\lambda$ ist, wobei λ die Wellenlänge der sich ausbreitenden Schallwelle ist.

12. System nach Anspruch 9, wobei der analytische Ausdruck in geschlossener Form für die räumliche Korrelationsfunktion eine Lambertsche Streugesetzfunktion umfaßt.

50

13. System nach Anspruch 12, wobei die räumliche Korrelationsfunktion definiert ist, wie folgt:

55

$$R = \frac{e^{i\psi}}{2 \sum_{l=0}^L b_l I_{l0}^0 P_l(\cos\beta)} \times [(2\pi/r)^{1/2} \sum_{l=0}^L b_l [P_l(\cos\beta) \sum_{j=0}^{\infty} i^{-j} I_{lj}^0 J_{j+1/2}(r) P_j(\cos\eta) + 2 \sum_{m=1}^l P_l^m(\cos\beta) (-1)^m \cos[m(\phi_0 - \alpha)] \sum_{j=m}^{\infty} i^{-j} I_{lm}^0 J_{j+1/2}(r) P_j^m(\cos\eta)]]$$

wobei

$\psi = k[v_x(a_4 - a_1) + v_y(a_5 - a_2) + v_z(a_6 - a_3)]/c$ der Ausdruck für eine Korrektur der Phase ist, die zu Streckenunterschieden der Größenordnung v/c gehört, wobei v die Wassergeschwindigkeit und c die Geschwindigkeit des Schalls im Wasser ist,

L eine obere Grenze einer Summation ist,

b_n ein Legendrepolynom-Koeffizient ist,

I_{lm}^m Ringgeometrikoeffizienten sind, die definiert sind, wie folgt:

$$I_{lj}^m = (1/2 + j) \frac{(l-m)! (j-m)!}{(l+m)! (j+m)!} \int_0^\pi \sin\theta \cos\theta P_l^m(\cos\theta) P_j^m(\cos\theta) d\theta,$$

wobei

l ein Platzhalterindex ist, über den summiert wird,

j ein Platzhalterindex ist, über den summiert wird,

m ein Platzhalterindex ist, über den summiert wird,

P ein Legendrepolynom ist,

β der Nadirneigungswinkel des Meeresbodens ist,

$r = (2\pi/\lambda) \times$ der gesamten Dreiachsenstrecke die Verzögerung vom bistatischen Punkt ($2\tau v_x, 2\tau v_y, 2\tau v_z$) ist, wobei λ die Wellenlänge der sich ausbreitenden Schallwelle ist und τ eine Zeitverschiebung ist,

J eine Besselfunktion ist,

$\cos \eta$ das Negative der vertikalen Verzögerung von dem bistatischen Punkt weg ist,

$\phi_0 - \alpha$ der Azimutwinkel ist, der zum Verhältnis der wegführenden Strecke hinsichtlich der y -Verzögerung zur x -Verzögerung ist, die vom Azimutwinkel weg aufgenommen ist, unter dem der Meeresboden geneigt ist.

14. System nach Anspruch 12, wobei die räumliche Korrelationsfunktion definiert ist, wie folgt:

$$R = \frac{(2\pi/r)^{1/2} e^{i\psi}}{2 \sum_{l=0}^L b_l I_{l0}^0} \times [\sum_{l=0}^L b_l \sum_{j=0}^{\infty} i^{-j} I_{lj}^0 J_{j+1/2}(r) P_j(\cos\eta)]$$

wobei

$r = (2\pi/\lambda) \times$ die gesamte Dreiachsenstrecke der Verzögerung die Verzögerung vom bistatischen Punkt ($2\tau v_x, 2\tau v_y, 2\tau v_z$) ist, wobei λ die Wellenlänge der sich ausbreitenden Schallwelle und τ eine Zeitverschiebung ist,

v_x die Wassergeschwindigkeit längs der x -Achse,

v_y die Wassergeschwindigkeit längs der y -Achse,

v_z die Wassergeschwindigkeit längs der z -Achse ist,

$\psi = k[v_x(a_4 - a_1) + v_y(a_5 - a_2) + v_z(a_6 - a_3)]/c$ der Ausdruck für eine Korrektur hinsichtlich der Phase zu Phasendifferenzen der Ordnung v/c gehörend ist, wobei v die Wassergeschwindigkeit und c die Geschwindigkeit des

Schalls im Wasser ist,
 L eine obere Grenze für eine Summation ist,
 b_n ein Legendrepolynom-Koeffizient ist,
 I_{lj}^m Ringgeometriekoeffizienten sind, die definiert sind, wie folgt:

$$I_{lj}^m = (1/2+j) \frac{(1-m)!(j-m)!}{(1+m)!(j+m)!} \int_0^{\pi} \sin \theta \cos \theta P_l^m(\cos \theta) P_j^m(\cos \theta) d\theta$$

wobei

θ der Winkel der gemessenen Energie von der Achse der Wellenausbreitung weg ist,

m als Null angenommen wird,

l ein Platzhalterindex ist, über den summiert wird,

j ein Platzhalterindex ist, über den summiert wird,

J eine Besselfunktion ist,

P ein Legendrepolynom ist, und

$\cos \eta$ das Negative der vertikalen Verzögerung vom bistatischen Punkt weg ist.

15. System nach Anspruch 9, wobei der analytische Ausdruck in geschlossener Form für die räumliche Korrelationsfunktion eine Kirchhoffannäherung für die Streugesetzfunktion umfaßt.

16. System nach Anspruch 15, wobei die räumliche Korrelationsfunktion definiert ist, wie folgt:

$$R = \frac{e^{i\phi}}{2 \sum_{l=0}^L b_l I_{l0}^0 P_l(\cos \beta)} \times [(2\pi/r)^{1/2} \sum_{l=0}^L b_l [P_l(\cos \beta) \sum_{j=0}^{\infty} i^{-j} I_{lj}^0 J_{j+1/2}(r) P_j(\cos \eta) + 2 \sum_{j=1}^{\infty} P_l^m(\cos \beta) (-1)^m \cos[m(\phi_0 - \alpha)] \sum_{j=m}^{\infty} i^{-j} I_{lj}^m J_{j+1/2}(r) P_j^m(\cos \eta)]]$$

wobei

I_{lj}^m Ringgeometriekoeffizienten sind, die definiert sind, wie folgt:

$$I_{lj}^m = (1/2+j) \frac{(1-m)!(j-m)!}{(1+m)!(j+m)!} \int_0^{\pi} \sin \theta \sigma(\theta) P_l^m(\cos \theta) P_j^m(\cos \theta) d\theta$$

wobei

$$\sigma(\theta) = \frac{R_{l0}^2}{4\pi \sin^2(\theta) \cos^2(\theta)} \int_0^{\infty} du u J_0(u) \exp(-qu^{2a})$$

θ der Winkel der gemessenen Energie von der Achse der Wellenausbreitung weg ist,
 R_{l0} ein Reflexionskoeffizient ist,

u eine Variable ist, über die integriert wird,
J eine Besselfunktion ist,

$$q = 2^{(1-2\alpha)} k^{(2-2\alpha)} \cos^2(\theta) C_h^2 \sin^{-2\alpha}(\theta),$$

wobei

q eine beliebige Variable ist, die zum Vereinfachen der Gleichung gewählt wurde,

$$k = 2\pi/\lambda$$

λ die Wellenlänge der sich ausbreitenden Schallwelle ist

C_h eine Strukturkonstante ist, die manchmal auch als ein Strukturfunktionsparameter bezeichnet wird, und
 α der effektive relative Winkel des Azimuts ist.

17. System nach Anspruch 9, wobei der analytische Ausdruck geschlossener Form für die räumliche Korrelationsfunktion eine allgemeine Funktion für Bandzustände ist.

18. System nach Anspruch 17, wobei die Magnitude der räumlichen Korrelationsfunktion definiert ist, wie folgt:

$$R = \frac{R_{\text{Spitze}}}{\{1 + (2^{a^2} - 1)[2(X - X_0)/W]^2\}^{1/a^2}}$$

wobei

R_{Spitze} die räumliche Spitzenkorrelation ist,

a ein Schenkelparameter ist, der das Ausmaß des Kurvenschenkels spezifiziert,

x ein Wert der Krümmung ist,

X_0 die Mitte der Krümmung ist, und

W der Breitenparameter einer Winkelstreuungsfunktion ist, der als das Zweifache der Strecke von der Mitte zum 1/2-Kurvenhöhenpunkt definiert ist.

19. Verfahren zum Messen von Geschwindigkeiten unter Verwendung eines Korrelationssonarsystems mit einem sendenden Wandler (208) und einer Vielzahl von empfangenden Wandlern (210), wobei das Verfahren die Schritte des Sendens eines Energieimpulses (110) in der Richtung einer reflektierenden Oberfläche, und des Empfangens des Impulsenergieechos (110') bei jedem empfangenden Wandler als einen Satz empfangener Werte aufweist, wobei das Verfahren ferner eine Maximum-Likelihood-Verarbeitung zum Abschätzen der Geschwindigkeit unter Verwendung korrelierter Werte, aufweist, gekennzeichnet durch

- das Berechnen von Korrelationswerten aus den empfangenen Werten, die zu vielen der empfangenden Wandler gehören;
- Bereitstellen anfänglicher Abschätzungen eines Satzes unbekannter Parameter; und
- eine Maximum-Likelihood-Verarbeitung der Korrelationswerte und der anfänglichen Abschätzungen von Parametern zum Maximieren der Wahrscheinlichkeit des Systems, das einen bestimmten Satz von Parametern aufweist, die den Korrelationswerten zugeordnet sind.

20. Verfahren nach Anspruch 19, zusätzlich den Schritt des Auswählens eines Codes zum Codieren der Impulsenergie aufweisend.

21. Verfahren nach Anspruch 20, wobei der Code abhängig von der relativ gemessenen Geschwindigkeit ausgewählt wird.

22. Verfahren nach Anspruch 20, wobei der Code abhängig von der Strecke zur reflektierenden Oberfläche ausgewählt

wird.

23. Verfahren nach Anspruch 19, wobei die Energie zu einer Vielzahl reflektierender Oberflächen hin gerichtet wird und die Schritte wiederholt werden, bis eine bestimmte reflektierende Oberfläche lokalisiert ist.

24. Verfahren nach Anspruch 23, wobei die Lage der bestimmten reflektierenden Oberfläche durch Anwenden eines angepaßten Filters bestimmt wird.

25. Verfahren nach Anspruch 19, wobei der Satz unbekannter Parameter eine Geschwindigkeitskomponente umfaßt.

26. Verfahren nach Anspruch 19, wobei der Maximum-Likelihood-Verarbeitungsschritt einen Simplexalgorithmus umfaßt.

27. Verfahren nach Anspruch 19, wobei der Maximum-Likelihood-Verarbeitungsschritt das Berechnen des natürlichen Logarithmus der Wahrscheinlichkeitsfunktion bei der anfänglichen Abschätzung von Parametern und bei jedem Parameter, durch einen Offset variiert, aufweist.

28. Verfahren nach Anspruch 19, wobei die empfangenen Werte und Korrelationswerte komplexe Zahlen sind.

Revendications

1. Système sonar à corrélation (200), qui possède un transducteur d'émission (208) servant à émettre une énergie acoustique sur une surface réfléchissante, un moyen générateur d'impulsion servant à produire une unique impulsion (110) d'énergie électrique à destination du transducteur d'émission, une pluralité de transducteurs de réception (210) servant à recevoir un écho d'impulsion (110') de la part de la surface réfléchissante, une pluralité de démodulateurs (222), chaque démodulateur étant connecté à l'un des transducteurs de réception et produisant un ensemble de valeurs, et un moyen d'application de probabilité maximale permettant d'estimer la vitesse à l'aide de valeurs corrélées, caractérisé en ce qu'il comporte en outre :

un moyen (230) servant à déterminer par autocorrélation lesdites valeurs pour chaque transducteur de réception, et à effectuer une intercorrélation entre différents transducteurs de réception, à un ou plusieurs temps de retard prédéterminés moindres que la largeur d'impulsion.

2. Système selon la revendication 1, où l'impulsion comprend une pluralité d'éléments codés.

3. Système selon la revendication 2, où chaque élément codé comprend une pluralité de cycles de porteuses.

4. Système selon la revendication 3, où chaque élément codé comprend plus de deux et moins de dix cycles de porteuses.

5. Système selon la revendication 2, où les éléments codés sont codés en phase.

6. Système selon la revendication 5, où les éléments codés sont codés avec des phases de 0° ou bien de 180°.

7. Système selon la revendication 2, où l'impulsion comporte des ensembles d'éléments de code non identiques de façon à produire des zéros de part et d'autre d'un retard de crête d'autocorrélation présélectionné.

8. Système selon la revendication 1, où l'impulsion possède une crête d'autocorrélation temporelle au temps de retard prédéterminé.

9. Système sonar à corrélation (200), qui possède un moyen servant à produire une impulsion (110) dans un liquide possédant des surfaces réfléchissantes, une pluralité de transducteurs (210) servant à recevoir le signal d'écho (110') créé par l'impulsion venant en contact avec les surfaces réfléchissantes, et un moyen d'application de probabilité maximale servant à maximiser la probabilité d'un ensemble de paramètres présélectionnés, comportant au moins une composante de vitesse, ayant des ensembles de corrélations indicatifs d'un état de paramètres, ledit système étant caractérisé en ce qu'il comprend en outre :

un moyen de corrélation servant à former des corrélations du signal d'écho reçu par chaque transducteur à un temps de retard prédéterminé avec le signal d'écho reçu par le même transducteur à un ou plusieurs autres

temps de retard, et avec les signaux d'écho reçus par les autres transducteurs à un ou plusieurs des autres temps de retard, lesdites corrélations permettant la mise en relation spatiale des transducteurs.

10. Système selon la revendication 9, où le moyen de corrélation comporte un moyen permettant de calculer des corrélations du signal d'écho à l'aide d'une fonction de corrélation spatiale définie comme suit :

$$R = \sum_{n=0}^{n_{\max}} b_n R_n$$

où:

b_n est un coefficient de polynôme de Legendre,

R_n est une fonction de corrélation spatiale faisant intervenir le $n^{\text{ième}}$ terme du diagramme de faisceau $W(\theta)$, $W(\theta)$ est le diagramme de faisceau du système, et

θ est l'angle d'énergie mesurée par rapport à l'axe de propagation des ondes.

11. Système selon la revendication 10, où l'expression analytique de forme fermée pour R_n est définie comme suit :

$$R_n = e^{i\Psi} \left\{ \left[\frac{2\pi}{\delta} \right]^{1/2} (1/2+n) i^{-n} J_{1/2+n}(\delta) P_n(\cos \varepsilon) \frac{1}{2n+1} + \right.$$

$$\left. \left[\frac{2\pi}{\delta} \right]^{1/2} \sum_{\substack{k=1 \\ \text{impair}}}^{\infty} (1/2+k) i^{-k} J_{1/2+k}(\delta) \right.$$

$$\times P_k(\cos \varepsilon) (-1)^{(n+k-1)/2} \frac{(n-1)!! k!!}{n!! (k-1)!! [k(k+1)-n(n+1)]} \text{ si } n \text{ est pair}$$

$$\left[\frac{2\pi}{\delta} \right]^{1/2} \sum_{\substack{k=0 \\ \text{pair}}}^{\infty} (1/2+k) i^{-k} J_{1/2+k}(\delta)$$

$$\times P_k(\cos \varepsilon) (-1)^{(n+k-1)/2} \frac{(k-1)!! n!!}{k!! (n-1)!! [n(n+1)-k(k+1)]} \text{ si } n \text{ est impair } \}$$

où:

n est le $n^{\text{ième}}$ terme du diagramme de faisceau,

$\Psi = k [v_x (a_4 - a_1) + v_y (a_5 - a_2) + v_z (a_6 - a_3)] / c$, qui est l'expression relative à la correction apportée à la phase correspondant à des différences de trajet d'ordre v/c , où v est la vitesse de l'eau et c est la vitesse du son dans l'eau,

$\delta = (2\pi/\lambda) \times$ la distance totale, suivant les trois axes, pour le retard par rapport au point bistatique, où λ est la longueur d'onde de l'onde sonore propagée,

J est une fonction de Bessel,

P est un polynôme de Legendre,

ε est un angle de phase décrivant la contribution relative du déplacement vertical et horizontal, et

$k = 2\pi/\lambda$, où λ est la longueur d'onde de l'onde sonore propagée.

12. Système selon la revendication 9, où l'expression analytique sous forme fermée relative à la fonction de corrélation spatiale comporte une fonction de loi de diffusion de Lambert.

13. Système selon la revendication 12, où la fonction de corrélation spatiale est définie comme suit :

$$R = \frac{e^{i\Psi}}{2 \sum_{l=0}^L b_l I_l^0 P_l(\cos\beta)} \times$$

$$[(2\pi/r)^{1/2} \sum_{l=0}^L b_l [P_l(\cos\beta) \sum_{j=0}^{\infty} i^j I_{lj}^0 J_{j+1/2}(r) P_j(\cos\eta) +$$

$$2 \sum_{m=1}^l P_l^m(\cos\beta) (-1)^m \cos[m(\varphi_0 - \alpha)] \sum_{j=m}^{\infty} i^j I_{lj}^m J_{j+1/2}(r) P_j^m(\cos\eta)]]$$

où:

$\Psi = k [v_x (a_4 - a_1) + v_y (a_5 - a_2) + v_z (a_6 - a_3)]/c$, qui est l'expression relative à une correction apportée à la phase correspondant à des différences de trajet d'ordre v/c , où v est la vitesse de l'eau et c est la vitesse du son dans l'eau,

L est une limite supérieure pour la sommation,

b_n est un coefficient de polynôme de Legendre,

I_{lj}^m désigne des coefficients de géométrie annulaire définis comme suit :

$$I_{lj}^m = (1/2+j) \frac{(l-m)! (j-m)!}{(l+m)! (j+m)!} \int_{\theta_1}^{\theta_2} \sin\theta \cos\theta P_l^m(\cos\theta) P_j^m(\cos\theta) d\theta,$$

où

l est un indice fictif sur lequel la sommation est effectuée,

j est un indice fictif sur lequel la sommation est effectuée,

m est un indice fictif sur lequel la sommation est effectuée,

P est un polynôme de Legendre,

β est l'angle d'inclinaison du fond marin par rapport au nadir,

$r = (2\pi/\lambda) \times$ la distance totale, par rapport aux trois axes, pour le retard par rapport au point bistatique ($2\tau v_x$, $2\tau v_y$, $2\tau v_z$, où λ est la longueur d'onde de l'onde sonore propagée, et τ est un décalage temporel,

J est une fonction de Bessel,

$\cos\eta$ est la valeur négative du retard vertical par rapport au point bistatique,

$\varphi_0 - \alpha$ est l'angle azimutal correspondant au rapport de la distance d'écartement sur le retard y à la distance d'écartement sur le retard x , indexé par rapport à l'angle azimutal suivant lequel le fond de la mer est incliné.

14. Système selon la revendication 12, où la fonction de corrélation spatiale est définie comme suit :

$$R = \frac{(2\pi/r)^{1/2} e^{i\Psi}}{2 \sum_{l=0}^L b_l I_{10}^0} \times \left[\sum_{l=0}^L b_l \sum_{j=0}^{\infty} i^j I_{1j}^0 J_{j+1/2}(r) P_j(\cos \eta) \right]$$

où :

$r = (2\pi/\lambda) \times$ la distance totale, suivant les trois axes, pour le retard par rapport au point bistatique ($2\tau v_x$, $2\tau v_y$, $2\tau v_z$), où λ est la longueur d'onde de l'onde sonore propagée, et τ est un retard temporel,

v_x est la vitesse de l'eau suivant l'axe x,
 v_y est la vitesse de l'eau suivant l'axe y,
 v_z est la vitesse de l'eau suivant l'axe z,

$\Psi = k [v_x (a_4 - a_1) + v_y (a_5 - a_2) + v_z (a_6 - a_3)]/c$, qui est l'expression relative à la correction apportée à la phase correspondant à des différences de trajet d'ordre v/c , où v est la vitesse de l'eau et c est la vitesse du son dans l'eau,

L est une limite supérieure pour la sommation,

b_n est un coefficient de polynôme de Legendre,

I_{ij}^m sont des coefficients de géométrie annulaire définis comme suit :

$$I_{lj}^m = (1/2+j) \frac{(l-m)! (j-m)!}{(l+m)! (j+m)!} \int_{\theta_1}^{\theta_2} \sin \theta \cos \theta P_l^m(\cos \theta) P_j^m(\cos \theta) d\theta$$

où

θ est l'angle de l'énergie mesurée par rapport à l'axe de la propagation de l'onde,

m est pris égal à zéro,

l est un indice fictif sur lequel la sommation est effectuée,

j est un indice fictif sur lequel la sommation est effectuée,

J est une fonction de Bessel,

P est un polynôme de Legendre, et

$\cos \eta$ est la valeur négative du retard vertical par rapport au point bistatique.

15. Système selon la revendication 9, où l'expression analytique sous forme fermée relative à la fonction de corrélation spatiale comporte une approximation de Kirchhoff pour la fonction de loi de diffusion.

16. Système selon la revendication 15, où la fonction de corrélation spatiale est définie comme suit :

$$R = \frac{e^{i\Psi}}{2 \sum_{l=0}^L b_l I_{l0}^0 P_l(\cos\beta)} \times$$

$$[(2\pi/r)^{1/2} \sum_{l=0}^L h_l [P_l(\cos\beta) \sum_{j=0}^{\infty} i^j I_{lj}^0 J_{j+1/2}(r) P_j(\cos\eta) +$$

$$2 \sum_{m=1}^l P_l^m(\cos\beta) (-1)^m \cos[m(\varphi_0 - \alpha)] \sum_{j=m}^{\infty} i^j I_{lj}^m J_{j+1/2}(r) P_j^m(\cos\eta)]]$$

où

I_{lj}^m sont des coefficients de géométrie annulaire définis comme suit :

$$I_{lj}^m = (1/2 + j) \frac{(l-m)! (j-m)!}{(l+m)! (j+m)!} \int_{\theta_1}^{\theta_2} \sin \theta \sigma(\theta) P_l^m(\cos\theta) P_j^m(\cos\theta) d\theta$$

où

$$\sigma(\theta) = \frac{R_{l0}^2}{4\pi \sin^2(\theta) \cos^2(\theta)} \int_0^{\infty} du u J_0(u) \exp(-qu^2\alpha)$$

θ est l'angle de l'énergie mesurée par rapport à l'axe de propagation de l'onde,

R_{l0} est un coefficient de réflexion,

u est une variable sur laquelle l'intégration est effectuée,

J est une fonction de Bessel,

$$q = 2(1-2\alpha) k(2-2\alpha) \cos^2(\theta) C_h^2 \sin^{-2\alpha}(\theta)$$

où

q est une variable arbitraire choisie pour simplifier l'équation,

$k = 2\pi/\lambda$,

λ est la longueur d'onde de l'onde sonore propagée,

C_h est une constante de structure, quelquefois appelée paramètre de fonction de structure, et

α est l'angle relatif effectif de l'azimut.

17. Système selon la revendication 9, où l'expression analytique sous forme fermée pour la fonction de corrélation spatiale comprend une fonction générale pour des formes en bandes.

18. Système selon la revendication 17, où l'amplitude de la fonction de corrélation spatiale est définie comme suit :

$$R = \frac{R_{peak}}{\{1 + (2^{a^2} - 1)[2(X - X_0)/W]^2\}^{1/a^2}}$$

5

où

R_{peak} est la corrélation spatiale de crête,

a est un paramètre de section spécifiant l'étendue de la section de courbe,

10

x est une valeur sur la courbe,

X_0 est le centre de la courbe, et

W est le paramètre de largeur d'une fonction de diffusion angulaire définie comme deux fois la distance du centre au point à ni-hauteur de la courbe.

15

19. Procédé de mesure de vitesses à l'aide d'un système sonar à corrélation possédant un transducteur d'émission (208) et une pluralité de transducteurs de réception (210), le procédé comprenant les opérations consistant à émettre une impulsion d'énergie (110) dans la direction d'une surface réfléchissante, et à recevoir l'écho d'énergie d'impulsion (110') en chacun des transducteurs de réception sous la forme d'un ensemble de valeurs reçues, le procédé comprenant en outre un traitement d'application de probabilité maximale permettant d'estimer la vitesse à l'aide de valeurs corrélées, caractérisé par les opérations suivantes :

20

calculer des valeurs de corrélation à partir des valeurs reçues associées à plusieurs des transducteurs de réception ;

25

produire des estimations initiales d'un ensemble de paramètres inconnus ; et

effectuer un traitement d'application de probabilité maximale sur les valeurs de corrélation et des estimations initiales de paramètres afin de maximiser la probabilité du système d'avoir un ensemble particulier de paramètres étant donné les valeurs de corrélation.

30

20. Procédé selon la revendication 19, comprenant en outre l'opération qui consiste à sélectionner un code afin de coder l'énergie d'impulsion.

21. Procédé selon la revendication 20, où on choisit le code en fonction de la vitesse mesurée relative.

35

22. Procédé selon la revendication 20, où on choisit le code en fonction de la distance à la surface réfléchissante.

23. Procédé selon la revendication 19, où l'énergie est dirigée vers une pluralité de surfaces réfléchissantes et on répète les opérations jusqu'à ce qu'une surface réfléchissante particulière soit localisée.

40

24. Procédé selon la revendication 23, où la localisation de la surface réfléchissante particulière est faite par utilisation d'un filtre apparié.

25. Procédé selon la revendication 19, où l'ensemble de paramètres inconnus comporte une composante de vitesse.

45



26. Procédé selon la revendication 19, où l'opération d'application de probabilité maximale comporte un algorithme simple.

27. Procédé selon la revendication 19, où l'opération d'application de probabilité maximale comporte l'évaluation du logarithme naturel de la fonction de probabilité pour l'estimation initiale des paramètres et pour chaque paramètre ayant subi un décalage.

50

28. Procédé selon la revendication 19, où les valeurs reçues et les valeurs de corrélation sont des nombres complexes.

55






FIG. 2




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8A




FIG. 8B




FIG. 8C




FIG. 9B




FIG. 9A





FIG. 10

FIG. 11a








FIG. 11b

FIG. 12a





TO EVALUATE $g_2(V_X, V_Y, V_Z, r_1)$

- 1)

LOOP $i = 1, 8$
 LOOP $j = 1, 8$
 $XLAG = x(j) - x(i)$; $YLAG = y(j) - y(i)$
 CALL WATCOR OR NORMR
 $B(i, j) = \text{ANSWER FROM MODEL}$
- 2) INVERT 16×16 RHO MATRIX AND OBTAIN $\det(RHO)$ USING LUDCMP, LUBKSB, INVERT, FASTIV
- 3) FORM TRACE $(RHO \text{ DATA } RHO^{-1} \text{ MODEL})$
- 4) $g_2 = \ln | \det(RHO) | + \text{MODEL}$
 Trace $(RHO \text{ DATA } RHO^{-1} \text{ MODEL})$

FIG. 12b